

WIRED BLUETOOTH DAYLIGHT HARVESTING KIT

SPECIFICATIONS

SENSOR:
Input Voltage: DC 12V
Output Current: 10mA Max
Output Power: 0.1W
Dimming: Class 2, 0-10V DC 10mA Max
Sinking Current: 10mA Max
Bluetooth Transmit: 100ft Max
Radio Frequency: 2.4GHz ± 75MHz
Bluetooth Version: 4.2
Housing Material: UL 94-5VA, Indoor Use Only
Detection Range: 40ft Max
Mounting Height: 18ft Max
Operating Temperature: -30°C to 55°C, -22°F to 131°F
Storage Temperature: -30°C to 85°C, -22°F to 185°F
IP Rating: IP20
Color: White
Warranty: Limited Lifetime
Comply to UL8750, UL1376, RoHS
Safety: cULus Listed LED Controller E504054
FCC ID: 2A26YLTKTVT2021
DID: D057145
DLC: NLTRC5KL0TN



FEATURES

The SMRT Wired Bluetooth Daylight Harvesting Kit, is a PIR Motion Sensor as well as a Daylight Harvesting Sensor. It comes complete with Power Pack with Low Voltage Quick Connect. PIR Motion Sensor & Recess Mounting Adapter, Wired 3 Button Wall Switch, Junction box for the Power Pack & Wall Switch & Wire Nuts. For details on the Power Pack, refer to the SMRT-PP10-DIM-BT data sheet. The SMRT Daylight Harvesting Kit is easy to set up in the SMRT APP with our powerful Bluetooth network. It's small scale goes virtually unnoticed on the ceiling, yet is powerful in performance.

DIMENSIONS / WIRING / DETAILS

