

personal  comfort.®



**WIRELESS REMOTE INSTRUCTIONS**

## Two wireless remotes

- Air control unit can have two remotes connected
- Remote will function for selected side until user makes a change

## Single remote option

- You can also setup the air control unit to be operated by one wireless remote
- Single remote option is required for single sleeper, queen, full, double twin xl and twin sized number beds



## Side of the bed

- Select side of bed for function
- Pump can utilize two remotes
- Remote will function for selected side until user makes a change

\*Side of the bed is based on laying in bed on your back.

## Operation

- First press turns on remote / LCD
- Select Firm or Soft
- Firm = pump inflates chamber
- Soft = pump deflates chamber
- Press or "press and hold", display will show changing value
- Once stopped, adjustment will be made after two seconds
- While adjusting, arrow will flash
- Cancel any operation by pressing any key



Right

Left



Left side of the bed

Right side of the bed

Firm adjustment

Soft adjustment

## Simultaneous use

- If adjustment is being made on one side, the other side will wait until completion

In this case, the bed is currently adjusting on the left side. Right side has made a request, and it will begin once left side has completed.



## Memory

- Set favorite setting or recall
- Press and hold 5 seconds to record current
- Press once to recall stored setting
- Two memory settings for each side

Memory Settings



## Connection

- Remotes will work out of the box
- Pump will accept connection for one minute after power up
- Press the 1 and 2 buttons at the same time for 3 seconds to enter pairing mode
- Pair will display, then counts down from 30 to 0
- If power is lost, remotes will connect automatically when power is restored

Press both 3 seconds



## Low battery indicator

- Uses two AAA Alkaline
- Estimated battery life:

Average capacity of AAA battery (mAh)	1250
Remote current in operation mode (mA)	45
Assumed remote active on period (Second)	60
Remote power consumption of each period (mAh)	0.75
Battery life (Number of cycles remote can be used)	1333

Note: Average capacity 1250mAh refers to the battery brand ENERGIZER.

