

SPARKLE

61" Sparkle Wall Panel



Installation Guidelines

NunoErin®

CUSTOMER SERVICE / ASSISTANCE
 +1 601.994.0023 support@nunoerin.com
 info@nunoerin.com www.nunoerin.com

Product Specifications

Product Name:
 61" Sparkle Wall Panel
Model: SPWP-AAA-61
Dimensions: 61.5" x 28.5" x 3.75"

Power Cord located in foam packaging

Caution: Unit is heavy
 Two people are required to safely install this unit
 Please read all instructions completely prior to installing

Materials Specifications

Display: Full Spectrum LED Lights
Touch: Capacitive Touch Sensors
Top Surface: Translucent white solid surface
Frame: Opaque white solid surface sides
Mounting: Heavy duty Z-Clip mounting brackets
Temperature: Operation: 0~50 C, Storage: -20 / 60 C
Weight (Panel only): 144 lbs.


Electrical – Power

Power Cord: USA 3-pin plug NEMA 5-15P
 Right Angle to IEC C13 Right Angle,
 16 AWG, Length 2 feet
Powersupply / AC Input:
 Voltage Range: 90 ~ 132 VAC
 (Universal AC Input / Full Range)
 AC Current: 1.2A / 115 VAC
 Frequency Range: 47 ~ 63 Hz



LPS IP67

Parts Included



1
 Wall Mount
 Z-Clip



1
 5/16" Hex Key

Tools to Use










1
 Phillips Head
 Screwdriver




1
 Power Drill

NOTE:
 Wall brackets must be mounted to studs
 or blocking in the wall, using the
 appropriate size and type of hardware for
 the wall construction, and must be capable
 of supporting the panel weight of
 approximately 280 pounds.




- 1 Install recessed duplex receptacle on target wall using the dimensions shown.




- 2 Install Z-Clips provided for wall mounting.

Use Appropriate hardware for wall type.



NOTE: Z-clips must be secured to studs or blocking to ensure that the weight of the panel is fully supported.




- 3** With panel held close to wall attach power cord.



- 4** Align panel over the Wall Mount Z-Clips.



- 5** Move panel firmly down to securely engage with the Wall Mount Z-Clips.




- 6** **WARNING:**
Do Not Skip This Step

Remove plastic cap on bottom of panel to access security latch hex nut.

Use 5/16" hex key provided to secure and lock panel into place.

After locking security latch, place plastic cap over hole to prevent access.



- 7** When the Sparkle Panel is first powered on, it will flash a pattern for approximately 10 seconds while calibrating to the ambient conditions, then the interactive programs will begin to play.





61" Sparkle Wall Panel



CLEANING AND MAINTENANCE

Spray with a multi-surface cleaner and wipe using a soft cloth as needed.

Recommended surface cleaners include Fantastik household cleaner, Formula 409 household cleaner, a neutral detergent or isopropyl alcohol with a min 70% concentration.

DO NOT USE ANY KIND OF CHEMICAL SOLVENT, ACIDIC OR ALKALI SOLUTION.

For disinfecting, Sani-Cloth® AF3 Germicidal Disposable Wipes, Steris Coverage Plus® and Clorox Healthcare® Hydrogen Peroxide Cleaner Disinfectant Wipes are also recommended.

DO NOT USE STRONG ACIDIC OR SOLVENT BASED CLEANERS, SUCH AS METHYL-CHLORIDE OR ACETONE.



ELECTRICAL

This product is for use on a nominal 100-220V circuit and must be plugged into an appropriate outlet that is properly installed and grounded in accordance with all local codes and ordinances.

NOTE: IMPROPER CONNECTION OF EQUIPMENT GROUNDING CONDUCTOR CAN RESULT IN A RISK OF ELECTRIC SHOCK. Check with a qualified electrician or serviceman if you are in doubt as to whether the product is properly grounded. Do not modify the plug provided with the product or if it will not fit the outlet, have a proper outlet installed by a qualified electrician.

INSTALLATION OF NUNOERIN PRODUCTS: Installation of all NunoErin is solely the responsibility of the builder, contractor, interior design and décor vendor, or the Customer. NunoErin has no control over the installer or the installation process and will not be responsible for any installations that are not done in a good, workmanlike manner, that do not follow NunoErin installation recommendations noted in the Product Literature or that fail to conform to electrical codes. NunoErin assumes no responsibility for such compliance. Consult your local building code officials for specific requirements.

Note: No NunoErin representative, dealer or salesperson is authorized to assist in the measurement of installation of NunoErin Products in the field. Customers are advised to obtain the proper measurements, specifications and sizes only from their builder, designer or engineer. Accordingly, any assistance provided in the field by a NunoErin representative should not be relied upon and will not be binding upon NunoErin in any form or fashion. NunoErin shall not be liable in any form of measures from incorrect measurements or specifications made in the field, irrespective of whether a NunoErin representative was involved in the process.

NunoErin®

533 Commerce Street
Jackson, MS 39201 USA

O: 01.601.944.0023 Customer Service: support@nunoerin.com

Confidential Information © NunoErin.