



STROBESWITCH

STROBESWITCH by TOMAR will allow first responders to gain access quickly to your gated community, home or commercial building when they are needed most.

WWW.TOMAR.COM

[f](#) [in](#) [@](#) [tomarUSA](#)



2795-2 STROBESWITCH™ Specifications

| Item | Description |
|-------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Range | 200 feet typical, but depends on intensity of optical emitter |
| Field of View | 10° vertical, 90° horizontal |
| Signal Acquisition Time | 0.64 seconds |
| Function Indicator | The unit has a red LED that illuminates whenever a proper optical signal is received. The LED is visible thru the viewport and can be seen for 25 feet or more. This feature can be used with the optional Hand Held Tester to verify the unit's operation. |
| 1790M-2 Power Module | 12-24VDC AC/DC DPDT relay output 2A @ 30VDC, 0.6A @ 120VAC 0-30 minute time delay plus continuous latch mode Remote reset |

- Range is 200 feet typical
- 0 - 30 minute time delay
- Detects & accepts all brands of emergency & transit priority control emitters.

SSLC-2 Low Current Detector Specifications

| Item | Description |
|------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Range | 200 feet typical, but depends on intensity of optical emitter |
| Field of View | 60° conical |
| Signal Acquisition Time | 1.5 seconds |
| Function Indicator | SSLC has an internal LED function which allows the installer to confirm proper function at time of installation. |
| Input Power Output rating | 12VDC 4mA idle current, 24VDC 2mA idle current, 24VAC 5mA idle current SPST solid-state relay output 100mA @ 120VAC 0-30 minute time delay plus test mode |
| Multiple Directions | Multiple SSLC-2 detectors can be paralleled to activate gate opener from multiple directions |

TOMAR ELECTRONICS, INC. • 2100 W. OBISPO AVE GILBERT, AZ 85233 USA • TEL: 800-338-3133 • FAX: 800-688-6627

WWW.TOMAR.COM





 @tomarUSA