

BCH-220 Handheld Radio

Introducing the new BCH-220 Handheld Radio for 1.25m 220 MHz. It's just what you need in a 220 MHz portable. The BCH-220 is small, durable, light weight and has excellent battery life. You can easily adjust the power from 5 watts down to 2 watts. It has 199 programmable channels to store all your favorites and it sounds great too. The BCH-220 fits nicely in the palm of your hand and has a bright easy to read LCD display. Make your next handheld radio a BCH-220!

The BCH-220 includes a Battery, Antenna, Belt Clip, Charger Base and Wall Plug. Other accessories available.



Specification

General	BCH-220
Frequency Range	219-260 MHz Rx 222.0-224.995 Tx
RF Output Power	Hi Power 5W Low Power 2W
Channels	199 Channels
Channel Spacing	Wide: 25kHz Narrow: 12.5kHz
CTCSS/DCS	50 CTCSS/105 DCS
Antenna Impedence	50Ω
Operating Temperature	-22° F to +140° F (-30° C to +60° C)
Operating Voltage	DC7.4V
Battery Type	1600mAh Li-ion
Battery Lifespan (5/5/90)	12 Hours
Dimensions (Excluding Antenna)	110.5(H) 58.5(W)35.6(D)mm
Weight (Battery, Antenna Included)	230g

Transmitter	BCH-220
Output Power	5W
Modulation	F3E
Spurious and Harmonics	≤ -65dB
FM Noise	≤ -45
Adjacent Channel Power	≤ -65dB
Audio Distortion	≤ 5%
Receiver	BCH-220
Sensitivity	≤ -123dBm @ 25kHz
Selectivity	-65dB
Intermodulation	≤ -60dB
Block	≥ 84dB
Rated Power Output	750mW@16Ω
Rated Audio Distortion	5%

In our on-going commitment to quality, specifications are subject to change without notice.