

MRE019

3 Way Signal Splitter

Description

MRE019 is designed to split mobile signals from the output of repeater to up to 3 indoor coverage antennas.

It is perfect for applications that require coverage of three different areas from a single repeater base unit.



Key Features

Divide the signal output and feed up to 3 indoor coverage antennas

Divided single strength from the repeater output in thirds

Suitable for GSM850, GSM900, GSM1800 and 3G

Electrical Specifications

Frequency Range	800-2500 MHz
Insertion Loss	$\leq 5.1\text{dB}$
Fluctuation	$\leq 0.3\text{ dB}$
VSWR	≤ 1.25
Amplitude Balance	$\leq 0.3\text{dB}$
Impedance	50 ohm
Power	200W
Connector Type	N Femal

Mechanical Specifications

Operating temperature	-35~+75 centigrades
Humidity	$\leq 95\%$
Dimension (DXH)	60 x 234 MM
Weight	530 Gram

