

# PHOENIX

## CLEAN POWER SUPPLY



The Walrus Audio Phoenix is a 15-Output isolated power supply, utilizing two internal custom wound toroidal transformers to provide a high level of noise rejection, giving artists the purest sound in their signal chain. The Phoenix is housed in a solid die cast enclosure and is 9.75" long x 2.6" wide x 2" high and has the following outputs available:

8 - 9V 100mA • 4 - 9V 300mA • 1 - 18V/9V 100mA • 2 - 12V/9V 100mA

The Phoenix comes with a detachable 120V AC power cord. The 120VAC includes a complimentary power outlet for unique pedals with proprietary power adapters. You can also use it to plug in cell phone chargers, lights, etc. This unit comes with 15, 2.1mm barrel black power cables and 2 black-to-red (line 6) power cables.



### VOLTAGE RATING

The voltage rating for your pedal must be 9VDC (direct current), do not use the Phoenix for AC (alternating current pedals). Most effects pedals are designed for 9VDC power, however, you should always check first or you could risk destroying your pedal. You can plug an individual adapter into the 120VAC courtesy output to power pedals with uncommon power requirements.

### POLARITY

For all standard effects pedals with center negative 2.1mm barrels, you can use the Black-to-Black barrel connectors. Specifically, for Line 6 pedals, you will have to use the Black-to-Red connectors. If you have a question about the voltage requirement of your pedal or which output to use, email [customerservice@walrusaudio.com](mailto:customerservice@walrusaudio.com).

### CURRENT DRAW

If the current requirement for your pedal is between 100mA - 300mA, you will need to use the 300mA outputs. For anything less than 100mA, you can use the 100mA outputs. Note: using the high current output on a low current draw pedal will work fine and not hurt the pedal. Refer to your pedal's manual for its specific requirements.

### WARRANTY

The Phoenix comes with a limited lifetime warranty for workmanship and components. Warranty does not include misuse or accidents resulting in damage. Warranty is not transferable or assignable and will only be issued to the original owner. Valid with receipt showing date of purchase. Contact [repairs@walrusaudio.com](mailto:repairs@walrusaudio.com) to receive an RMA number before returning product.

### WARNING

Before connecting your effects pedal to the Phoenix, you must first verify the power requirements for your pedal. Input Voltage Requirements - 120V (60Hz). This product will be destroyed if any other input voltage is used, voiding the warranty. If the backplate is opened, the warranty is immediately voided. For repairs, troubleshooting or questions, contact us at [repairs@walrusaudio.com](mailto:repairs@walrusaudio.com). Never plug an amplifier or any other device that is rated over 200 watts into the 120V courtesy power input. Do not attempt to fix defective unit yourself. Contact Walrus Audio at [repairs@walrusaudio.com](mailto:repairs@walrusaudio.com) for help.



Standard 2.1mm  
9VDC plug for  
most effects pedals



Standard 2.1mm  
9VDC Jack



Negative-to-Ground