

A guide to assembling your Bulldog Clip Buttons




STEP 1

- Assemble your button as usual: inserting the shell, [1a] laying your artwork on top, [1b] and placing the mylar on top. [1c]



STEP 2

- Swivel die around until it stops. [2a]
- Rotate clip so that it points directly across to the other edge. [2b, 2c]
- Place a penny inside of the clip. [2d] This will ensure that the clip is flat when placing it into the die. [2e]
- Place clip into die making sure that the bump is facing to the top of the die. [2f]
- Push down on the handle as far as the machine allows. [2g]



STEP 3

- Swivel die around until it stops. [3a]
- Push down on the handle as far as the machine allows. [3b]
- Remove clip button from machine. [3c]



STEP 4

- Turn button around, and remove the penny from the clip [4a]
- Twist the clip around so that it faces upwards or away from the button. [4b]
- The button is now ready to be clipped as seen in [4c].

