



# EL60WR-H Installation Instructions

## Product Overview:

The Eagle Equalizer eliminates hyper flash when installing LED turn signals on pre-2014 Harley Davidson models. Only one unit is needed for either 2 or all 4 turn signals.

## Typical Installation

Normal installation requires only a few tools and takes less than 15 minutes.

### Required Tools



- Philips-Head Screwdriver

## Installation Warning

If you feel uncomfortable installing this product, we recommend having a professional complete the installation. Eagle Lights LLC is not liable for any damage to the product or vehicle due to an improper installation. If you have questions about the installation, please feel free to call us at 1-800-921-3162 or email us at Support@EagleLights.com.

## Installation:

Below are steps for a typical installation on most Harley Davidson models. Steps may be different depending on the model. Please ensure you have read through the instructions and understand them clearly before attempting the installation.

 <b>WARNING!</b> 
<ul style="list-style-type: none"><li>• To prevent possible electrical shock, disconnect the negative battery terminal before installing this product.</li></ul>

1. Remove the seat from the motorcycle. A flat head or phillips head screwdriver may be required.
  
2. Locate the rear wiring harness on your model.
  - a. 96 - '10 Softails, '97 - '11 Dynas, '99 - '03 Sportsters, '06 - '09 Street Glide, '97 - '09 Road Glide Standard, '97 - '13 Touring Models, and '10 - '13 Tri-Glide -

- i. The plug will be located under the seat and look like the plug in the picture. Disconnect the harness. If a run / brake / turn module is installed, the equalizer must be installed before it.



- b. Plug in harness in between the two plugs.
3. Test the function of the turn signals.
  
  4. Using the included zip ties, fasten the unit to a frame rail away from other wiring. Fasten the unit by placing the zip ties over the wire portion. Do not place it over the load resistors section as it can become hot under prolonged use.