

CGCT-AU-SWT-B5-D07 MANUAL



MODEL	CGCT-AU-SWT-B5-D07
VOTAGE (V)	3V DC
BATTERY TYPE	1X CR2032
MAX. NUMBER OF DEVICES	64 Bluetooth Devices
OPERATING RANGE	10 - 20 m
MAX. AMBIENT TEMPERATURE LIMITS	-20°C~ +45°C
IP RATING	IP20 (Use in dry locations only)
PROTOCOL	Bluetooth 4.2 Mesh

PLEASE NOTE:
-All Devices and remotes out of the box are assigned to group 1, so all devices can work together immediately with no additional set up. If you have multiple remotes you can assign specific remotes to control specific groups of lights (i.e. in different rooms).
Please Note: Each remote can only be assigned to one group of lights.

Warranty
The warranty is invalid in the case of improper use, tampering, and removal of the U.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the warranty period it will be replaced free of charge, this is subject to correct installation and return of the faulty product. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Aurora reserves the right to alter specifications without prior notice.

STANDARD FUNCTION:

RESET DEVICE:

Hold on/off buttons until LED flashes 3 times.

ASSIGN LIGHTS & REMOTE TO A ROOM

1

To group lights to a single remote, turn all your Bluetooth Devices off. Turn back on the lights that you wish to control with this specific remote,

2

Within 10 seconds of the lights being turned on, hold the central bulb button (⬤) and a scene preset button (1, 2, 3, 4, 5, or 6). For example, button 2, will assign that group into group 2. As there are 6 buttons you can create 6 independent groups.

3

Lights and remote will flash 3 times. They can now be controlled independently from other devices.

REPLACING THE BATTERY

1

2