

ST-HBD02

MANUAL

Lamptitude



1. The lamp must be installed in rated voltage and assure safety earth.
2. Installing and fixing the lamp should be processed by professional under the condition power off.
3. When change the lamp bulb please noted that the max wattage shouldn't exceed the labeled wattage.
4. If the external electrical wire damage please change by the professional in time in case of any danger.

Rated voltage: In accordance with the product labeled
Rated power: In accordance with the product labeled



MAINTENANCE AND CLEANING

1. Please turn off the power before cleaning the luminaire to avoid any risk of high voltage electric shock.
2. Please contact the supplier and do not disassemble it by yourself when there is any defect or damage of luminaire.

1

阅读说明书。
Read the instructions.

2

查看配件包是否有以下配件：
Check if the accessory bag has the following accessories:

1. 自攻螺丝 Self-tapping screw —— 2PCS

2. 毛根塞/壁虎 Plug —— 2PCS

关闭电源 Power off.

3

将灯具两侧螺丝松开，将安装底盘从灯体旋出；在墙壁上定位打孔，在孔位中打入壁虎，将安装底盘用螺丝锁好固定在墙面上。
Unscrew both sides of luminaire, screw out the mounting plate from the luminaire; position and punch holes on the wall, insert plugs into the holes, and fix the mounting plate on the wall with screws.

4

接线，棕“火线”，蓝“零线”，黄绿“地线”。
Wiring: Brown wire with "Live", blue wire with "Neutral", yellow green wire with "Grounding".

注意：接线处做防水处理！
Attention: Waterproof wire connections!

5

将灯体按螺旋方向旋紧在底盘上，并锁好两侧的螺丝。
Tighten the luminaire on the mounting plate according to the spiral direction And lock the screws on both sides.

6

打开开关进行测试。
Turn on the switch to test.

OFF
ON