



SKUTT
CERAMIC PRODUCTS

MODEL FIREBOX 8x4 MTS

SPECIFICATIONS

Two and a half inch thick lid, base & walls
Maximum Temperature: cone 10, 2350 °F

Electrical Requirements

115 volt
15.0 amps
1800 watts

Wiring Requirements

Copper wire size: #12
Fuse or Breaker: 20
Receptacle: 2 pole, 3 wire grounding
Nema 5-20R configuration

UL listed and CSA approved.

WARRANTY: Two Year Parts & Labour



LOCATING YOUR KILN

*Place the kiln to the left of the proper electrical outlet,
so the cord can be plugged in without touching the metal jacket.*

*Remove all flammable materials such as curtains, plastics, paper
or shelves in the area of the kiln, and allow at least 18 inches of space
between the kiln and walls.*

*Fire the kiln on the stand provided. Air circulation is necessary
to prevent overheating.*

PHYSICAL DIMENSIONS

Firing Chamber - .17 cubic feet
Opening: 8 x 8 inches
Depth: 4.5 inches

** Please allow 18 inches surrounding all sides*

THE SOUNDING STONE
Pottery Supplies
104 Trottier Bay
Winnipeg, MB
R3T 3Y5
Ph (204) 284-2964
Fax 453-5210
www.soundingstone.com