

# SERIES 7500E WATT DUAL FUEL PORTABLE GENERATOR





## SERIES 7500E WATT DUAL FUEL PORTABLE GENERATORS

Ideal for use at outdoor events, the next DIY project or emergency backup power in the case of an outage, the Generac GP7500E Dual Fuel provides power and versatility when and where you need it. Featuring Dual Fuel functionality, the GP7500E DF is capable of running on either gasoline or an LP gas fuel source with the simple turn of a dial.











## **CONTROL PANEL**

### **HOUR METER**

Tracks maintenance intervals

### (2) 1-POLE 20A

Circuit Breakers

### (1) 120/240V AC

30A L14-30R Twist Lock Outlet



### **ELECTRIC START**

Provides reliable, hassle free startups (battery included)

### (2) 120V, 20A

5-20R GFCI Duplex Outlets

### 2-POLE 30A

Circuit Breaker

### **HOW MUCH POWER DO YOU NEED?**

Sizing a portable generator is easy. Check out this sample:

- Choose which devices you want to power at the same time.
- Record and add the running watts listed for each device that you need to power.
- Record the starting watts listed for each device.
- Select the one device with the highest starting watts. Add that number to the total running watts to determine the total wattage requirement.

DEVICE	RUNNING WATTS	ADDITIONAL STARTING WATTS	GENERATOR SIZE	
Refrigerator	700	2200	Minimum starting watts for your needs	
Sump Pump	1050	2150		
Belt Sander	1200	2400		
Circular Saw	1400	2300	6750 starting watts	
Total	4350	+ 2400 =		

	DEVICE	RUNNING WATTS	ADDITIONAL STARTING WATTS		
	Coffee Maker	1500	-		
	Computer with a 17" Monitor	800	-		
	Electric Range - 8" Element	2100	-		
	Electric Water Heater	2000	1000		
ноизеногр	Garage Door Opener - 1/2 HP	875	2350		
	Microwave - 1000 Watts	1000	-		
	Refrigerator/Freezer	700	2200		
	Sump Pump 1/2 HP	1050	2150		
	Television - 27"	500	-		
	Washing Machine	1150	2300		
	Well Pump - 1/2 HP	1000	2100		
	Central AC - 24,000 BTU	3800	4950		
	Furnace Fan Blower - 1/2 HP	875	2300		
	Heat Pump	4700	4500		
	Window AC - 12,000 BTU	3250	3950		
	Air Compressor - 1/2 HP	1000	2000		
	Airless Paint Sprayer- 1/3 HP	600	1200		
JOBSITE	Belt Sander - 3"	1200	2400		
	Circular Saw - 7-1/4"	1400	2300		
	Hand Drill - 1/2"	600	900		
	Reciprocating Saw	960	-		
	Quartz Halogen Work Light	1000	-		
	Table Saw, 10"	2000	2000		
RECREATION	CD / DVD Player	100	-		
	Color TV - 13"	150	-		
	Inflator Pump	50	150		
	Outdoor Light String	250	-		
	Slow Cooker	250	-		
	RV Air Conditioner (13,500 BTU)	1500	700		

\*Watts listed are approximate. Check your appliance for actual requirements. Total wattage requirements assumes intermittent starting of devices.

SERIES	GP7500E DF		
SPECIFICATIONS			
Model Number	8011		
Running Watts	7500 (Gas) / 6800 (LP)		
Starting Watts	9400 (Gas) / 8500 (LP)		
Rated AC Voltage	120 / 240 VAC		
Rated AC Frequency	60 Hz		
Rated VAC Frequency	62.5 / 31.25		
Engine Displacement	420cc		
Engine Type	OHV		
Engine RPM	3600		
Recommended Oil	10W-30 / SAE 30		
Oil Capacity Qt (L)	1.06 (1.0)		
Lubrication Method	Splash Lube		
Automatic Voltage Regulation (AVR)	Yes		
Starting Method	Electric Start / Pull Start		
Low Oil Shutdown	Yes		
Battery Included	Yes		
Start Switch Type	Off / Run / Start Switch		
Fuel Gauge	Built-In Tank		
Fuel Tank Capacity Gal (L)	7.9 (29.9)		
Run Time @ 50% Load	10 (Gas) / 5 (LP)*		
Handle Style	Dual Grip, Single Folding with Lock Pin		
Wheel Type	9.5" Never Flat		
Warranty	3 Year Limited (Residential) / 2 Year Limited (Commercial)		
DIMENSIONS & WEIGHTS			
Length in (mm)	27.18 (690.3)		
Width in (mm)	27 (684)		
Height in (mm)	27.09 (688)		
Carton Length in (mm)	33.46 (850)		
Carton Width in (mm)	22.44 (570)		
Carton Height in (mm)	26.38 (670)		
Unit Weight lbs (kg)	204 (92.5)		
Shipping Weight lbs (kg)	229 (103.8)		

<sup>\*</sup>When using a 20 lb. LP tank

