- 1. Enable P2P at DVR(configuration)
- 2. Create a Verification code

	Configuration
anet Access General PPF	OE NTP Email SNMP NAT More Settings
nable Cloud P2P	
Inable Stream Encryption	
Verification Code	WWWWEE K
Enable DDNS DDNS Type Server Address Device Domain Name User Name Password	1 2 3 4 5 6 7 8 9 0 Q W E R 7 V U I O P A S 0 F G H J K L Image: Z X C V 8 N M Image: Z X C V 8 N M Image: Z X C V 8 N M
	Apply Back

3. Go to Guarding Expert, Click Cloud P2P



4. Click +

••••• T-Mobile LTE 11:21 AM 🛞 🕈 85% 🔳			
E Cloud P2P +			
Devices	Acc	ount	
WH-D5216(492	610113)	>	
Camera No.: 18			

5. Scan the QR Code on the case or box (We will have this sticker from the next shipment)



6. Or manually key in the serial number



7. You can find out the serial number at DVR->Maintenance It's the 9 digit number (492610113 for example)

Vice Info Camera Record Alarm Network HDD Device Name Embedded Net DVR Model WH-D5216 Serial No. V3.1.2, Build 150314
Device Name Embedded Net DVR Model WH-D5216 Serial No. 1620141206AAWR492610113W V3.1.2, Build 150314 V3.1.2
Model WH-D5216 Serial No. 1620141206AAWR492610113W V3.1.2, Build 150314 V3.1.2, Build 150314
Serial No. 1620141206AAWR492610113W
V3.1.2, Build 150314
Firmware Version vs o Build 141218
Encoding Version V5.0, Build RATE
Verification Code

8. Enter the verification code from step 2



9. Start live view

Alias	WH-D5216/492610113)
Allds	WH-05210(492010115)
Camera No.	18
	Start Live View



10. Note: It only allows one login per time!!