

ConfigureCmd(Bi-Direction):

FPort: 0x07

Bytes	1	1	Var(Fix =9 Bytes)
	CmdID	DeviceType	NetvoxPayLoadData

ConfigReportReq	R718 CJ2/C K2/C	0x01	0x15/ 16/1	MinTime (2bytes Unit:s)	MaxTime(2bytes Unit:s)	BatteryChange(1byte Unit:0.1v)	TemperatureChange(2byte Unit:0.1°C)	Reserved (2Bytes,Fixed 0x00)
-----------------	-----------------------	------	---------------	-------------------------------	-------------------------------	-----------------------------------	--	------------------------------------

For example,

To set report interval time as 5 minutes:

1st byte(01): CmdID — ConfigReportReq

2nd byte(16): DeviceType — R718CK2

3rd 4th byte(012C): MinTime — 300 sec

5th 6th byte(012C): MaxTime — 300 sec

7th byte(01): BatteryChange — 0.1 V (report while voltage increase or reduce 0.1V)

8th 9th byte(000A): TemperatureChange — 0.1°C (report while temperature increase or reduce 0.1 °C)

10th 11th byte(0000): Reserved

The payload will be: 0116012C012C01000A0000