

## ADC-V723

### **SPECIFICATIONS**

RECORDING COMPRESSION H.264

INGRESS PROTECTION

IP66

MAX RESOLUTION 1920 x1080

IMAGE SENSOR 1/2.7" CMOS, 2.1 MP, 1920 x1080

LENS / ANGLE OF VIEW 3.0 mm, F2.0, 117°

LOW-LIGHT SENSITIVITY

O lux with IR

IR RANGE

Up to ~40 ft (12 m)

IMAGE ADJUSTMENTS
Flip, brightness, contrast,
saturation, sharpness, exposure

WIRELESS CONNECTIVITY 802.11 b/g/n/ac, 2.4 & 5 GHz

OPERATING TEMPERATURE -13°F - 113°F (-25°C - 45°C)

OPERATING HUMIDITY <95% Non-condensing

DIMENSIONS (L x W x H) 2.5 x 2.5 x 4.5" (6.4 x 6.4 x 11.4 cm)

### **REQUIREMENTS**

POWER

12 V - 1 A DC power adapter (included)

NETWORK

Wi-Fi (2.4 or 5 GHz) connection to broadband Internet



# 1080p Outdoor WI-FI Video Camera with HDR

Get smarter video alerts and high-quality live and recorded video with the ADC-V723. Powerful Video Analytics from Alarm.com can detect and alert you to people, vehicles, and animals entering your property. With a wide field of view, night vision, and High Dynamic Range (HDR), the ADC-V723 lets you see what's important – no matter the time of day or lighting conditions. Pair with an Alarm.com Stream Video Recorder for 24/7 local recording or with an Alarm.com security system for cloud-based alarm and sensor-triggered clip recordings (additional hardware required).

#### **FEATURES**

- 117° field of view
- High Dynamic Range (HDR)
- Wi-Fi (2.4 or 5 GHz)
- Waterproof & Dust-tight
- Works with the Alarm.com customer website and mobile app
- Video Analytics, Video Motion Detection, and sensor-triggered clips saved to the cloud
- Onboard Recording with Smart View

### **INCLUDED ACCESSORIES**

- Power Adapter
- Mounting Hardware

### **LED GUIDE**

	LED STATUS	DESCRIPTION
STATUS LED	Off	Power off
$\bigcirc$	Flashing Red	Power on, camera booting
	Flashing Green	Local network connection
	Solid Green	Connected to Alarm.com
	Blinking Blue	WPS mode
	Blinking White	Wi-Fi Access Point mode
TROUBLE CONDITION	Solid Red	No local or Intenet connection
FACTORY RESET	Alternating Red and Green	Camera resetting to factory default