

SUPERSEDES:
13-JAN-12


FRAME: 280T
BASIC TYPE: CT

PRINT:
07-2781-02

SHEET:
1 OF 1

Technical drawing of a circular electrical enclosure. The drawing shows a front view of the enclosure with a circular body, a central mounting hole, and a flange with mounting tabs. Dimensions are indicated by arrows and labeled as follows:

- A**: Overall diameter of the enclosure body.
- AB**: Distance from the center of the enclosure to the center of the mounting tab.
- AC**: Distance from the center of the enclosure to the center of the mounting tab, measured along the flange.
- D**: Distance from the center of the enclosure to the center of the mounting tab, measured along the flange.
- E**: Distance from the center of the enclosure to the center of the mounting tab, measured along the flange.
- 2E**: Distance between the centers of two mounting tabs.
- G**: Distance from the center of the enclosure to the center of the mounting tab, measured along the flange.
- J**: Distance from the center of the enclosure to the center of the mounting tab, measured along the flange.
- O**: Overall diameter of the enclosure body.
- T**: Thickness of the mounting tab.
- AF**: Distance from the center of the enclosure to the center of the mounting tab, measured along the flange.
- AA SIZE CONDUIT**: Label for the mounting tab.



		A	B	C	D - .06	E	2E ±.03	G	H +.05	J
	IN	14.00	13.00	27.00	7.00	5.50	11.00	1.00	.53	3.25
	MM	356	330	686	178	140	279	25	14	83

		N	O	P ²	T	U -.001	V MIN	W	AA	AB
IN		5.00	14.31	14.63	2.06	1.875	4.38	.50	2.00	13.00
MM		127	363	372	52	47.63	111	13		330

		AC	AF	BA	BS	ES MIN	EV	SQ KEY
	IN	9.69	3.25	4.75	5.50	3.28	1.00	.500
	MM	246	83	121	140	83	25	12.70

		FRAME	2F ±.03
	IN	284T	9.50
	MM		241
	IN	286T	11.00
	MM		279

1. DIMENSIONS MAY VARY BY .25" DUE TO CASTING AND/OR FABRICATION VARIATIONS.
2. LARGEST MOTOR WIDTH.
3. TOLERANCES SHOWN ARE IN INCHES ONLY.

4. CONDUIT BOX MAY BE LOCATED ON EITHER SIDE OF MOTOR
CONDUIT OPENINGS MAY BE LOCATED IN STEPS OF 90 DEGREES
REGARDLESS OF LOCATION. STANDARD AS SHOWN WITH
CONDUIT OPENING DOWN.

