

HV3728C Installation Instructions



PRODUCT SPECIFICATIONS		DIMENSIONS	IMAGE
Model No.	HV3728C		
Name	Array		
Material	Aluminium		
Colour	Powder Coated Black		
IP Rating	IP65		
Input Voltage	240V		
Lamp Base	Built in LED		
Lamp Wattage	30w		
CRI:	>80		
Wiring	Parallel		
Dimmable	No		
Warranty	2 Years Replacement		

Important Safety Issues:

- This product must be installed by a qualified electrician according to AS/NZS 3000.
- Ensure all electrical mains are disconnected before any installation.
- Do not exceed maximum wattage restrictions for globes: 240V GU10 = 35w / 12V MR16 = 20w
- Modification of this product will void any warranty.
- Havit Lighting does not take responsibility for wrong installation, incorrect use, or use of installation material that does not belong to the system.
- When installing low voltage fittings, Voltage to fitting must be within +or- 5% of voltage required, if not within this allowance warranty will be voided.
- Aluminium and 304SS fittings must not be installed within 2km of any salt water environments.
- When installing copper fittings, gloves must be worn to avoid any oils transferring to fitting.
- All 316 stainless steel fittings must have regular cleaning maintenance to avoid any tea staining from forming on fitting.
(Warranty does not cover Tea Staining)
- All o-rings and seals must be in place correctly to maintain warranty.

Steps for Installation:

1. Make sure that the electrical circuit is free of voltage (master switch off).
2. Mark position for the screw holes where the fitting is to be mounted, using the fitting bracket as a template.
3. Mount the bracket securely, using appropriate fixings and screws.
4. Cable can be plugged in directly using the flex and plug supplied.
5. Alternatively, cable can be hardwired. Connect earth first, then live and neutral wires.
6. If hardwiring, do not cut the cable any further back than the connection point. If done incorrectly, warranty will be void.
7. Adjust fitting to point at desired location, and then tighten nuts at side of fitting to hold in position.
8. All connections must be carried out carefully, inspect all contacts before switching back on the electric circuit.

Must be Installed by a Licensed Electrician

For More Information Contact Havit Lighting

143 Beauchamp Road
Matraville NSW 2036
Australia

Tel: 02 9381 8300
Fax: 02 9666 8881
Email: sales@havit.com.au
Web: www.havit.com.au