



Model: PowerMax+ Capacity: 10,000mAh  
 Size: 3.5" x 3.25" x 1.15" Weight: 9oz

**PowerMax+**  
 Input: AC100-240V 50/60Hz 0.3A or USB-C port  
 PowerDelivery 20W  
 Output: USB-C 5V/3A, 9V/2A, 12V/1.5A PD 20W  
 USB1 (colored): 5V/3A, 4.5V/5A, 9V/2A, 12V/1.5A  
 (QC 22.5W Max)  
 USB2: 5V/2.1A  
 Wireless Qi: 15W (Max)

**PowerMax+ Wall Charger (separated)**  
 Input: AC100-240V 50/60Hz 0.3A AC Charger 5V/2A  
 Output: USB-C port 5V/2A (10W)

**PowerMax+ Power bank (separated)**  
 Input: USB-C 5V/3A, 9V/2A, 12V/1.5A (PD 20W)  
 Output: USB-C 5V/3A, 9V/2A, 12V/1.5A (PD 20W)  
 USB1 (colored): 5V/3A, 4.5V/5A, 9V/2A, 12V/1.5A  
 (QC 22.5W Max)  
 USB2: 5V/2.1A  
 Wireless Qi: 15W (Max)

### FEATURES

- Power Delivery 20W USB-C Port
- Qualcomm 3.0 22.5W USB-A port
- 2.1Amp USB-A charging port
- 15W Qi certified wireless charging
- 10,000mAh rechargeable power bank capacity
- Removable wall charger with USB-C port (10W output)
- Digital power status screen display
- On/Off power switch button
- Foldable wall outlet prongs
- Compact and portable
- Charge 4 devices simultaneously
- Smart detection recognizes if your device is capable of fast charging and PowerMax+ auto matches its charging capacity
- Power Delivery/Fast charging is downgraded when more than one device is being charged via the PowerMax+ or when the PowerMax+ battery bank is charging/plugged in

### INSTRUCTIONS

- Auto turns on/starts charging when cable is plugged into PowerMax+ and into device
- One click activates all charging methods, must do this to turn on wireless charging
- Two clicks turns battery display on
- Two button clicks turns PowerMax+ off, even if plugged into device via cable
- Auto turns off after 30 seconds of no use
- Charge PowerMax+ by plugging it directly into wall outlet or via USB-C port. Power Delivery Fast Charging is downgraded when PowerMax+ plugged in and charging up.



LED display shows from 100 to 0 battery level status



0-99 flashing means PowerMax+ is being charged



100 flashing means PowerMax+ is fully charged



PD symbol means fast charging is on



Wireless charging symbol

### CAUTION

- Do not place charger into water or clean with wet cloth
- Keep charger safe from fire, flammable and explosive liquids and gases
- Avoid extreme drops, hits or shaking
- Use in safe temperature conditions 14°F to 113°F
- Avoid long exposure to direct sunlight, humidity and other extreme weather conditions
- We recommend charging PowerMax+ at least monthly if used infrequently
- Store in dry place in a mid-range power level (not recommended to store for long periods at full or zero power supply)
- Charge PowerMax+ with appropriate charger and adapter/cable, stop using if any sign of battery corrosion
- This is not a toy or suitable for children



**POWER MAX+**  
 6 in 1 Charging Station and  
 10,000mAh Power Bank