

JBC501F9QU(W)-Q87-B



1. Fanless Black Aluminum Enclosure
2. Socket LGA1150 Supporting 4th Generation Intel Core i3, i5, i7 Processors (35W)
3. Supports DDR3-1600 SODIMM up to 16GB
4. 1 * 2.5" SATA3 6Gb/s Internal Drive Bay
5. 1 * Full-size mSATA/mini-PCIE Shared Slot
6. 1 * Half-size mini-PCIE Slot (or WIFI installed)
7. 4 * USB 3.0 Ports, 2 * USB 2.0 Ports
8. 4 * COM Ports (1 * RS232/422/485, 3 * RS232)
9. Includes Wall Mount and DIN Rail Clips



Specifications

MB Model	JNF9QU-Q87
Part No	HBJC501F9QU-Q87-B (non-WIFI) HBJC501F9QUW-Q87-B (WIFI)
CPU/Chipset	<ul style="list-style-type: none"> ● INTEL® LGA 1150 Socket Core i7/i5/i3/Pentium Processor (35W) ● INTEL® Q87 express chipset
Memory	2 * 204-pin SO-DIMM slots supporting dual channel DDR3-1600 up to 16GB
Storage	<ul style="list-style-type: none"> ● 1 * 2.5" SATA3 6Gb/s internal drive bay ● 1 * Full-size mSATA/mini-PCI Express shared slot
Network	<ul style="list-style-type: none"> ● 1 * Intel i211AT Gigabit LAN, 1 * Intel i217LM Gigabit LAN with vPro & iAMT 9.0 support ● 1 * Half-size mini-PCIE slot (802.11 b/g/n + BT 4.0 installed in WIFI model)
Other Features	HD Audio, AHCI, Watchdog Timer 10-255 min/sec.
Rear Panel I/O	<ul style="list-style-type: none"> ● 4 * USB 3.0 ports ● 1 * HDMI ● 1 * DVI-D, 1 * VGA ● 2 * RJ45 ● Line-out, Mic-in ● 4 * COM (1 * RS232/422/485, 3 * RS232) ● 1 * +12V DC in (Lockable)
Front Panel I/O	<ul style="list-style-type: none"> ● 1 * Power button ● 1 * HDD LED ● 2 * USB 2.0 ports
Temperature	Operating Temperature: 0 ~ 40 ° C Storage Temperature: -20 ~ 85 ° C
Dimensions	260 (W) x 208 (D) x 58.5 (H) mm
OS Support	32/64 bit versions of Windows 7, Windows 8.1, Linux

Packing List:

Parts Number	Description	Set
-----	JBC501F9QU(W)-Q87-B	1
G01-DVI-VGA-BK-F	DVI to VGA adapter	1
G03-JC501QIG01-F	JBC501 Quick Installation Guide	1
G03-NF9QU-F	IPC NF9QU M/B User's Manual	1
G02-DVD15-A18-WF	INTEL 6 / 7 / 8 Series Driver DVD-ROM	1
L01AS039-F	Adapter 19V 6.32A 120W FSP120-REBN2 LEVEL6	1
-----	Power cord	1
HCS5XXMWM01B-F	JC5XX Wall mount / Black color	2
LCSCHBJC3XX-F	Screw Pack	3
J05-ANT-AN2400-F	Antenna2G4 -2dBi R-AN2400-5701RS (JBC501F9QUW-Q87-B only)	2
HCS3XXDINRAILPS-F	Din Rail Clip	2

External I/O:

