PURE OUTDOOR LIGHTING Pillar Lite ULTRA 50

PROJECT:

TYPE:

SOURCE:

NOTES:

SPECIFICATIONS




LED Chip	Cree CXA 2540 field replaceable LED board		
Luminaire Output	2800 Lumens minimum @ 700mA (26 watts), delivered from the Luminaire with unobstructed beam		
Lumens Per Watt	107 Lumens minimum @ 52 watts, delivered from Luminaire with unobstructed beam		
CRI (3000K)	80 Standard, 90+ Optional		
Colour Temperatures	2700K, 3000K, 4000K		
Beam Angles	13, 22, 33, 51		
Ingress Protection	IP66		

Warranty	Electronics = 5 years Body Aluminium = 5 years
Standards	BS/EN 60598.2.2 cUL 1598 CE



PRODUCT CONFIGURATION

Please fill in appropriate codes into boxes provided



ADDITIONAL COMMENTS:				
HUNZA PURE OUTDOOR LIGHTING	HUNZA FACTORY	130 Felton Mathew Ave Saint Johns Auckland 1072 New Zealand	Ph: +64-9-528 9471 Fax: +64-9-528 9361 hunza@hunza.co.nz www.hunzalighting.com	INTERNATIONAL CONTACTS: http://www.hunzalighting.com/contact.php Specifications may change without notice. This document contains proprietary information of Hunza. Its receipt or possession does not corvey an rights to reproduce or disclose its content.

LUMINAIRE CONSTRUCTION

CNC machined from one of the following metals:

Aluminium:

Base: 105mm (5%") solid aluminium rod. Body: 127mm (5") high corrosion resistant aluminium tube with chromate substrate and high UV resistant polyester powder coat. Colours: Black, Bronze, Silver Star, White, White Birch, Olive Green, Dark Grey, Corten.

Cable:

Water resistant rubber.

Gaskets:

Silicone, iron impregnated 220°C (428°F).

Step Lens:


12mm (1/2") extra clear, low iron, shatter resistant glass. Lifetime warranty.

Mounting:

The mounting plate is fixed to the surface using three stainless steel screws. The luminaire is then fixed to the mounting plate. A large Wall Plate is available for mounting over junction boxes.

Luminaire Weight:


8kg (17lb 10oz)




BEAM ANGLES

High efficiency Reflectors. Field replaceable

IES files available for download: http://www.hunzalighting.com/download.php



WIRING GUIDE



Diagrams are a guide only, wire colours and polarity may change depending on fixture and country

HUNZA FACTORY

130 Felton Mathew Ave


Saint Johns

Auckland 1072

New Zealand



Available for download: www.hunzalighting.com/download.php



 Specifications may change without notification
 Aug 2017

 Ph: +64-9-528 9471
 INTERNATIONAL CONTACTS:
 INTERNATIONAL CONTACTS:

 Fax: +64-9-528 9361
 http://www.hunzalighting.com/contact.php
 This document contains proprietary information of Huzza. Its receipt or possession does not convey any rights to reproduce or disclose its content.