

## Nominal Power Lumens (2200K CCT, 70 CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	3,408	4,178	5,172	5,673
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	100	95	89	86
<b>T2R</b>	Lumens	3,648	4,473	5,536	6,074
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	107	102	95	92
<b>T3</b>	Lumens	3,482	4,270	5,285	5,797
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	102	97	91	88
<b>T3R</b>	Lumens	3,540	4,342	5,374	5,896
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	104	99	93	89
<b>T4FT</b>	Lumens	3,508	4,302	5,324	5,840
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	103	98	92	88
<b>T4W</b>	Lumens	3,440	4,218	5,222	5,727
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	101	96	90	87
<b>SL2</b>	Lumens	3,413	4,185	5,179	5,681
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	100	95	89	86
<b>SL3</b>	Lumens	3,476	4,264	5,277	5,788
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	102	97	91	88
<b>SL4</b>	Lumens	3,321	4,073	5,040	5,528
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	98	93	87	84
<b>5NQ</b>	Lumens	3,579	4,387	5,431	5,958
	BUG Rating	B2-U0-G0	B2-U0-G0	B2-U0-G1	B2-U0-G1
	Lumens per Watt	105	100	94	90
<b>5MQ</b>	Lumens	3,707	4,545	5,627	6,172
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	109	103	97	94
<b>5WQ</b>	Lumens	3,621	4,442	5,496	6,029
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	106	101	95	91
<b>SLL/ SLR</b>	Lumens	3,074	3,770	4,667	5,120
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	90	86	80	78
<b>RW</b>	Lumens	3,557	4,363	5,399	5,924
	BUG Rating	B2-U0-G1	B2-U0-G1	B2-U0-G1	B3-U0-G1
	Lumens per Watt	105	99	93	90
<b>AFL</b>	Lumens	3,567	4,373	5,412	5,938
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	105	99	93	90

## Nominal Power Lumens (2700K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	3,876	4,754	5,882	6,452
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	114	108	101	98
<b>T2R</b>	Lumens	4,150	5,088	6,298	6,910
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	122	116	109	105
<b>T3</b>	Lumens	3,961	4,858	6,012	6,595
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	117	110	104	100
<b>T3R</b>	Lumens	4,027	4,939	6,114	6,706
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	118	112	105	102
<b>T4FT</b>	Lumens	3,991	4,895	6,057	6,643
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	117	111	104	101
<b>T4W</b>	Lumens	3,914	4,799	5,941	6,515
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	115	109	102	99
<b>SL2</b>	Lumens	3,882	4,762	5,892	6,462
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	114	108	102	98
<b>SL3</b>	Lumens	3,955	4,851	6,003	6,584
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	116	110	104	100
<b>SL4</b>	Lumens	3,779	4,632	5,734	6,290
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	111	105	99	95
<b>5NQ</b>	Lumens	4,072	4,991	6,179	6,777
	BUG Rating	B2-U0-G0	B2-U0-G1	B2-U0-G1	B2-U0-G1
	Lumens per Watt	120	113	107	103
<b>5MQ</b>	Lumens	4,218	5,172	6,401	7,022
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	124	118	110	106
<b>5WQ</b>	Lumens	4,120	5,052	6,253	6,859
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	121	115	108	104
<b>SLL/ SLR</b>	Lumens	3,497	4,289	5,309	5,824
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	103	97	92	88
<b>RW</b>	Lumens	4,047	4,963	6,142	6,739
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	119	113	106	102
<b>AFL</b>	Lumens	4,057	4,974	6,158	6,754
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	119	113	106	102

## Nominal Power Lumens (3000K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	4,222	5,176	6,406	7,027
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	124	118	110	106
<b>T2R</b>	Lumens	4,519	5,541	6,858	7,525
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	133	126	118	114
<b>T3</b>	Lumens	4,313	5,290	6,547	7,182
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	127	120	113	109
<b>T3R</b>	Lumens	4,386	5,378	6,657	7,303
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	129	122	115	111
<b>T4FT</b>	Lumens	4,346	5,330	6,596	7,235
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	128	121	114	110
<b>T4W</b>	Lumens	4,262	5,226	6,469	7,095
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	125	119	112	107
<b>SL2</b>	Lumens	4,227	5,185	6,416	7,038
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	124	118	111	107
<b>SL3</b>	Lumens	4,307	5,282	6,537	7,170
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	127	120	113	109
<b>SL4</b>	Lumens	4,115	5,045	6,245	6,849
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G3	B1-U0-G3
	Lumens per Watt	121	115	108	104
<b>5NQ</b>	Lumens	4,434	5,436	6,728	7,380
	BUG Rating	B2-U0-G0	B2-U0-G1	B2-U0-G1	B3-U0-G1
	Lumens per Watt	130	124	116	112
<b>5MQ</b>	Lumens	4,593	5,632	6,971	7,646
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	135	128	120	116
<b>5WQ</b>	Lumens	4,487	5,502	6,810	7,470
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	132	125	117	113
<b>SLL/ SLR</b>	Lumens	3,808	4,671	5,781	6,342
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	112	106	100	96
<b>RW</b>	Lumens	4,407	5,404	6,689	7,339
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	130	123	115	111
<b>AFL</b>	Lumens	4,418	5,417	6,705	7,356
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	130	123	116	111

## Nominal Power Lumens (5000K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	4,635	5,683	7,034	7,717
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	136	129	121	117
<b>T2R</b>	Lumens	4,962	6,084	7,531	8,262
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	146	138	130	125
<b>T3</b>	Lumens	4,736	5,808	7,189	7,886
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
<b>T3R</b>	Lumens	4,816	5,907	7,310	8,020
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	142	134	126	122
<b>T4FT</b>	Lumens	4,772	5,852	7,242	7,945
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	140	133	125	120
<b>T4W</b>	Lumens	4,679	5,738	7,103	7,791
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G2
	Lumens per Watt	138	130	122	118
<b>SL2</b>	Lumens	4,643	5,693	7,045	7,728
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G3
	Lumens per Watt	137	129	121	117
<b>SL3</b>	Lumens	4,729	5,800	7,178	7,873
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
<b>SL4</b>	Lumens	4,518	5,540	6,856	7,520
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G3	B1-U0-G3
	Lumens per Watt	133	126	118	114
<b>5NQ</b>	Lumens	4,868	5,969	7,387	8,104
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	143	136	127	123
<b>5MQ</b>	Lumens	5,043	6,184	7,654	8,396
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	148	141	132	127
<b>5WQ</b>	Lumens	4,926	6,041	7,476	8,201
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	145	137	129	124
<b>SLL/ SLR</b>	Lumens	4,181	5,129	6,348	6,964
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	123	117	109	106
<b>RW</b>	Lumens	4,839	5,934	7,345	8,058
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	142	135	127	122
<b>AFL</b>	Lumens	4,852	5,948	7,362	8,077
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	143	135	127	122

## Nominal Power Lumens (6000K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	4,635	5,683	7,034	7,717
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	136	129	121	117
<b>T2R</b>	Lumens	4,962	6,084	7,531	8,262
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	146	138	130	125
<b>T3</b>	Lumens	4,736	5,808	7,189	7,886
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
<b>T3R</b>	Lumens	4,816	5,907	7,310	8,020
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	142	134	126	122
<b>T4FT</b>	Lumens	4,772	5,852	7,242	7,945
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	140	133	125	120
<b>T4W</b>	Lumens	4,679	5,738	7,103	7,791
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G2
	Lumens per Watt	138	130	122	118
<b>SL2</b>	Lumens	4,643	5,693	7,045	7,728
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G3
	Lumens per Watt	137	129	121	117
<b>SL3</b>	Lumens	4,729	5,800	7,178	7,873
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
<b>SL4</b>	Lumens	4,518	5,540	6,856	7,520
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G3	B1-U0-G3
	Lumens per Watt	133	126	118	114
<b>5NQ</b>	Lumens	4,868	5,969	7,387	8,104
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	143	136	127	123
<b>5MQ</b>	Lumens	5,043	6,184	7,654	8,396
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	148	141	132	127
<b>5WQ</b>	Lumens	4,926	6,041	7,476	8,201
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	145	137	129	124
<b>SLL/ SLR</b>	Lumens	4,181	5,129	6,348	6,964
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	123	117	109	106
<b>RW</b>	Lumens	4,839	5,934	7,345	8,058
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	142	135	127	122
<b>AFL</b>	Lumens	4,852	5,948	7,362	8,077
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	143	135	127	122

## Nominal Power Lumens (2700K CCT, 80CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	3,408	4,178	5,172	5,673
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	100	95	89	86
<b>T2R</b>	Lumens	3,648	4,473	5,536	6,074
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	107	102	95	92
<b>T3</b>	Lumens	3,482	4,270	5,285	5,797
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	102	97	91	88
<b>T3R</b>	Lumens	3,540	4,342	5,374	5,896
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	104	99	93	89
<b>T4FT</b>	Lumens	3,508	4,302	5,324	5,840
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	103	98	92	88
<b>T4W</b>	Lumens	3,440	4,218	5,222	5,727
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	101	96	90	87
<b>SL2</b>	Lumens	3,413	4,185	5,179	5,681
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	100	95	89	86
<b>SL3</b>	Lumens	3,476	4,264	5,277	5,788
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	102	97	91	88
<b>SL4</b>	Lumens	3,321	4,073	5,040	5,528
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	98	93	87	84
<b>5NQ</b>	Lumens	3,579	4,387	5,431	5,958
	BUG Rating	B2-U0-G0	B2-U0-G0	B2-U0-G1	B2-U0-G1
	Lumens per Watt	105	100	94	90
<b>5MQ</b>	Lumens	3,707	4,545	5,627	6,172
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	109	103	97	94
<b>5WQ</b>	Lumens	3,621	4,442	5,496	6,029
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	106	101	95	91
<b>SLL/ SLR</b>	Lumens	3,074	3,770	4,667	5,120
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	90	86	80	78
<b>RW</b>	Lumens	3,557	4,363	5,399	5,924
	BUG Rating	B2-U0-G1	B2-U0-G1	B2-U0-G1	B3-U0-G1
	Lumens per Watt	105	99	93	90
<b>AFL</b>	Lumens	3,567	4,373	5,412	5,938
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	105	99	93	90

## Nominal Power Lumens (3000K CCT, 80CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
<b>LED Drive Current</b>		600mA	800mA	1A	1.2A
<b>Optics</b>					
<b>T2</b>	Lumens	3,684	4,517	5,590	6,132
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	108	103	96	93
<b>T2R</b>	Lumens	3,943	4,835	5,984	6,566
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	116	110	103	99
<b>T3</b>	Lumens	3,763	4,615	5,713	6,267
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	111	105	99	95
<b>T3R</b>	Lumens	3,827	4,694	5,809	6,373
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	113	107	100	97
<b>T4FT</b>	Lumens	3,792	4,650	5,756	6,313
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	112	106	99	96
<b>T4W</b>	Lumens	3,718	4,560	5,644	6,191
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	109	104	97	94
<b>SL2</b>	Lumens	3,690	4,524	5,598	6,141
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	109	103	97	93
<b>SL3</b>	Lumens	3,758	4,609	5,705	6,256
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	111	105	98	95
<b>SL4</b>	Lumens	3,590	4,402	5,448	5,976
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	106	100	94	91
<b>5NQ</b>	Lumens	3,868	4,742	5,871	6,441
	BUG Rating	B2-U0-G0	B2-U0-G1	B2-U0-G1	B2-U0-G1
	Lumens per Watt	114	108	101	98
<b>5MQ</b>	Lumens	4,007	4,913	6,082	6,672
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	118	112	105	101
<b>5WQ</b>	Lumens	3,914	4,801	5,941	6,517
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	115	109	102	99
<b>SLL/ SLR</b>	Lumens	3,323	4,076	5,044	5,535
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	98	93	87	84
<b>RW</b>	Lumens	3,844	4,716	5,837	6,403
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	113	107	101	97
<b>AFL</b>	Lumens	3,856	4,727	5,850	6,418
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	113	107	101	97

## Energy and Performance Data

### Nominal Power Lumens (2200K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

### Nominal Power Lumens (2700K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

### Nominal Power Lumens (3000K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

### Nominal Power Lumens (5000K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

### Nominal Power Lumens (6000K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

### Nominal Power Lumens (2700K CCT, 80 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

### Nominal Power Lumens (3000K CCT, 80 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25