

Nominal Power Lumens (2200K CCT, 70 CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	6,792	8,331	10,310	11,311
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	103	98	93	88
T2R	Lumens	7,273	8,918	11,039	12,110
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	110	105	99	95
T3	Lumens	6,942	8,513	10,537	11,559
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	105	100	95	90
T3R	Lumens	7,059	8,655	10,714	11,752
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	107	102	97	92
T4FT	Lumens	6,995	8,577	10,617	11,646
	BUG Rating	B1-U0-G2	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	106	101	96	91
T4W	Lumens	6,858	8,410	10,409	11,419
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	104	99	94	89
SL2	Lumens	6,804	8,344	10,326	11,328
	BUG Rating	B1-U0-G2	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	103	98	93	88
SL3	Lumens	6,931	8,500	10,520	11,541
	BUG Rating	B1-U0-G2	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	105	100	95	90
SL4	Lumens	6,620	8,118	10,049	11,024
	BUG Rating	B1-U0-G3	B1-U0-G3	B1-U0-G3	B1-U0-G3
	Lumens per Watt	100	96	91	86
5NQ	Lumens	7,134	8,749	10,830	11,880
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	108	103	98	93
5MQ	Lumens	7,392	9,063	11,218	12,306
	BUG Rating	B3-U0-G1	B3-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	112	107	101	96
5WQ	Lumens	7,221	8,855	10,958	12,021
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	109	104	99	94
SLL/ SLR	Lumens	6,129	7,517	9,303	10,205
	BUG Rating	B1-U0-G2	B1-U0-G3	B1-U0-G3	B2-U0-G3
	Lumens per Watt	93	88	84	80
RW	Lumens	7,092	8,696	10,764	11,807
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	107	102	97	92
AFL	Lumens	7,112	8,719	10,793	11,840
	BUG Rating	B1-U0-G1	B1-U0-G1	B2-U0-G1	B2-U0-G2
	Lumens per Watt	108	103	97	93

Nominal Power Lumens (2700K CCT, 70CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	7,726	9,477	11,728	12,866
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G3
	Lumens per Watt	117	111	106	101
T2R	Lumens	8,273	10,147	12,558	13,776
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	125	119	113	108
T3	Lumens	7,898	9,684	11,988	13,150
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	120	114	108	103
T3R	Lumens	8,029	9,846	12,188	13,370
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G3
	Lumens per Watt	122	116	110	104
T4FT	Lumens	7,957	9,759	12,078	13,250
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	121	115	109	104
T4W	Lumens	7,803	9,568	11,842	12,989
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G3
	Lumens per Watt	118	113	107	101
SL2	Lumens	7,740	9,492	11,748	12,887
	BUG Rating	B2-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	117	112	106	101
SL3	Lumens	7,885	9,671	11,967	13,130
	BUG Rating	B1-U0-G2	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	119	114	108	103
SL4	Lumens	7,532	9,236	11,432	12,540
	BUG Rating	B1-U0-G3	B1-U0-G3	B1-U0-G3	B1-U0-G3
	Lumens per Watt	114	109	103	98
5NQ	Lumens	8,116	9,953	12,320	13,515
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	123	117	111	106
5MQ	Lumens	8,410	10,310	12,762	14,000
	BUG Rating	B3-U0-G2	B3-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	127	121	115	109
5WQ	Lumens	8,215	10,072	12,466	13,675
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	124	118	112	107
SLL/ SLR	Lumens	6,973	8,551	10,583	11,611
	BUG Rating	B1-U0-G3	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	106	101	95	91
RW	Lumens	8,067	9,893	12,245	13,433
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	122	116	110	105
AFL	Lumens	8,089	9,919	12,279	13,469
	BUG Rating	B1-U0-G1	B1-U0-G1	B2-U0-G2	B2-U0-G2
	Lumens per Watt	123	117	111	105

Nominal Power Lumens (3000K CCT, 70CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	8,414	10,321	12,772	14,012
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G3	B2-U0-G3
	Lumens per Watt	127	121	115	109
T2R	Lumens	9,009	11,049	13,675	15,002
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	137	130	123	117
T3	Lumens	8,601	10,547	13,054	14,320
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	130	124	118	112
T3R	Lumens	8,744	10,722	13,272	14,559
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G3
	Lumens per Watt	132	126	120	114
T4FT	Lumens	8,666	10,627	13,153	14,428
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	131	125	118	113
T4W	Lumens	8,497	10,419	12,895	14,145
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G3	B2-U0-G3
	Lumens per Watt	129	123	116	111
SL2	Lumens	8,429	10,336	12,793	14,033
	BUG Rating	B2-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	128	122	115	110
SL3	Lumens	8,586	10,531	13,032	14,297
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	130	124	117	112
SL4	Lumens	8,201	10,058	12,449	13,656
	BUG Rating	B1-U0-G3	B1-U0-G3	B1-U0-G3	B2-U0-G4
	Lumens per Watt	124	118	112	107
5NQ	Lumens	8,838	10,839	13,415	14,718
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	134	128	121	115
5MQ	Lumens	9,158	11,228	13,898	15,246
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	139	132	125	119
5WQ	Lumens	8,945	10,968	13,575	14,892
	BUG Rating	B4-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	136	129	122	116
SLL/ SLR	Lumens	7,593	9,311	11,525	12,643
	BUG Rating	B1-U0-G3	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	115	110	104	99
RW	Lumens	8,785	10,773	13,335	14,627
	BUG Rating	B3-U0-G1	B3-U0-G2	B3-U0-G2	B4-U0-G2
	Lumens per Watt	133	127	120	114
AFL	Lumens	8,809	10,802	13,371	14,667
	BUG Rating	B1-U0-G1	B2-U0-G1	B2-U0-G2	B2-U0-G2
	Lumens per Watt	133	127	120	115

Nominal Power Lumens (5000K CCT, 70CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	9,240	11,332	14,025	15,386
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G3	B2-U0-G3
	Lumens per Watt	140	133	126	120
T2R	Lumens	9,893	12,132	15,016	16,473
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	150	143	135	129
T3	Lumens	9,444	11,581	14,334	15,723
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G3
	Lumens per Watt	143	136	129	123
T3R	Lumens	9,602	11,774	14,574	15,987
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G3	B2-U0-G3
	Lumens per Watt	145	139	131	125
T4FT	Lumens	9,516	11,669	14,442	15,843
	BUG Rating	B2-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	144	137	130	124
T4W	Lumens	9,329	11,441	14,159	15,533
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G3	B3-U0-G3
	Lumens per Watt	141	135	128	121
SL2	Lumens	9,255	11,350	14,048	15,409
	BUG Rating	B2-U0-G3	B2-U0-G3	B2-U0-G3	B3-U0-G3
	Lumens per Watt	140	134	127	120
SL3	Lumens	9,429	11,563	14,310	15,699
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	143	136	129	123
SL4	Lumens	9,006	11,044	13,670	14,996
	BUG Rating	B1-U0-G3	B1-U0-G3	B2-U0-G4	B2-U0-G4
	Lumens per Watt	136	130	123	117
5NQ	Lumens	9,706	11,902	14,731	16,160
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	147	140	133	126
5MQ	Lumens	10,055	12,329	15,260	16,740
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	152	145	137	131
5WQ	Lumens	9,822	12,044	14,907	16,353
	BUG Rating	B4-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	149	142	134	128
SLL/ SLR	Lumens	8,338	10,225	12,655	13,882
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	126	120	114	108
RW	Lumens	9,647	11,829	14,643	16,062
	BUG Rating	B3-U0-G1	B3-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	146	139	132	125
AFL	Lumens	9,674	11,861	14,681	16,106
	BUG Rating	B1-U0-G1	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	147	140	132	126

Nominal Power Lumens (6000K CCT, 70CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	9,240	11,332	14,025	15,386
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G3	B2-U0-G3
	Lumens per Watt	140	133	126	120
T2R	Lumens	9,893	12,132	15,016	16,473
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	150	143	135	129
T3	Lumens	9,444	11,581	14,334	15,723
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G3
	Lumens per Watt	143	136	129	123
T3R	Lumens	9,602	11,774	14,574	15,987
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G3	B2-U0-G3
	Lumens per Watt	145	139	131	125
T4FT	Lumens	9,516	11,669	14,442	15,843
	BUG Rating	B2-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	144	137	130	124
T4W	Lumens	9,329	11,441	14,159	15,533
	BUG Rating	B2-U0-G2	B2-U0-G2	B2-U0-G3	B3-U0-G3
	Lumens per Watt	141	135	128	121
SL2	Lumens	9,255	11,350	14,048	15,409
	BUG Rating	B2-U0-G3	B2-U0-G3	B2-U0-G3	B3-U0-G3
	Lumens per Watt	140	134	127	120
SL3	Lumens	9,429	11,563	14,310	15,699
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	143	136	129	123
SL4	Lumens	9,006	11,044	13,670	14,996
	BUG Rating	B1-U0-G3	B1-U0-G3	B2-U0-G4	B2-U0-G4
	Lumens per Watt	136	130	123	117
5NQ	Lumens	9,706	11,902	14,731	16,160
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	147	140	133	126
5MQ	Lumens	10,055	12,329	15,260	16,740
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	152	145	137	131
5WQ	Lumens	9,822	12,044	14,907	16,353
	BUG Rating	B4-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	149	142	134	128
SLL/ SLR	Lumens	8,338	10,225	12,655	13,882
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	126	120	114	108
RW	Lumens	9,647	11,829	14,643	16,062
	BUG Rating	B3-U0-G1	B3-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	146	139	132	125
AFL	Lumens	9,674	11,861	14,681	16,106
	BUG Rating	B1-U0-G1	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	147	140	132	126

Nominal Power Lumens (2700K CCT, 80CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	6,792	8,331	10,310	11,311
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	103	98	93	88
T2R	Lumens	7,273	8,918	11,039	12,110
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	110	105	99	95
T3	Lumens	6,942	8,513	10,537	11,559
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	105	100	95	90
T3R	Lumens	7,059	8,655	10,714	11,752
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	107	102	97	92
T4FT	Lumens	6,995	8,577	10,617	11,646
	BUG Rating	B1-U0-G2	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	106	101	96	91
T4W	Lumens	6,858	8,410	10,409	11,419
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	104	99	94	89
SL2	Lumens	6,804	8,344	10,326	11,328
	BUG Rating	B1-U0-G2	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	103	98	93	88
SL3	Lumens	6,931	8,500	10,520	11,541
	BUG Rating	B1-U0-G2	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	105	100	95	90
SL4	Lumens	6,620	8,118	10,049	11,024
	BUG Rating	B1-U0-G3	B1-U0-G3	B1-U0-G3	B1-U0-G3
	Lumens per Watt	100	96	91	86
5NQ	Lumens	7,134	8,749	10,830	11,880
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	108	103	98	93
5MQ	Lumens	7,392	9,063	11,218	12,306
	BUG Rating	B3-U0-G1	B3-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	112	107	101	96
5WQ	Lumens	7,221	8,855	10,958	12,021
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	109	104	99	94
SLL/ SLR	Lumens	6,129	7,517	9,303	10,205
	BUG Rating	B1-U0-G2	B1-U0-G3	B1-U0-G3	B2-U0-G3
	Lumens per Watt	93	88	84	80
RW	Lumens	7,092	8,696	10,764	11,807
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	107	102	97	92
AFL	Lumens	7,112	8,719	10,793	11,840
	BUG Rating	B1-U0-G1	B1-U0-G1	B2-U0-G1	B2-U0-G2
	Lumens per Watt	108	103	97	93

Nominal Power Lumens (3000K CCT, 80CRI)

Number of Light Squares		SA2A	SA2B	SA2C	SA2D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	7,342	9,006	11,145	12,226
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	111	106	100	96
T2R	Lumens	7,861	9,641	11,932	13,090
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	119	113	107	102
T3	Lumens	7,505	9,203	11,390	12,495
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	114	108	103	98
T3R	Lumens	7,630	9,356	11,581	12,704
	BUG Rating	B1-U0-G2	B1-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	116	110	104	99
T4FT	Lumens	7,562	9,272	11,476	12,590
	BUG Rating	B1-U0-G3	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	115	109	103	98
T4W	Lumens	7,413	9,092	11,251	12,343
	BUG Rating	B1-U0-G2	B2-U0-G2	B2-U0-G2	B2-U0-G2
	Lumens per Watt	112	107	101	96
SL2	Lumens	7,355	9,019	11,162	12,245
	BUG Rating	B1-U0-G2	B2-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	111	106	101	96
SL3	Lumens	7,493	9,188	11,371	12,475
	BUG Rating	B1-U0-G2	B1-U0-G3	B2-U0-G3	B2-U0-G3
	Lumens per Watt	114	108	102	97
SL4	Lumens	7,157	8,775	10,863	11,916
	BUG Rating	B1-U0-G3	B1-U0-G3	B1-U0-G3	B1-U0-G3
	Lumens per Watt	108	103	98	93
5NQ	Lumens	7,712	9,458	11,707	12,841
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	117	111	105	100
5MQ	Lumens	7,990	9,797	12,126	13,302
	BUG Rating	B3-U0-G2	B3-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	121	115	109	104
5WQ	Lumens	7,806	9,571	11,846	12,995
	BUG Rating	B3-U0-G2	B4-U0-G2	B4-U0-G2	B4-U0-G2
	Lumens per Watt	118	113	107	102
SLL/ SLR	Lumens	6,626	8,125	10,056	11,031
	BUG Rating	B1-U0-G2	B1-U0-G3	B1-U0-G3	B2-U0-G3
	Lumens per Watt	100	96	91	86
RW	Lumens	7,666	9,400	11,636	12,764
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	116	111	105	100
AFL	Lumens	7,687	9,425	11,667	12,799
	BUG Rating	B1-U0-G1	B1-U0-G1	B2-U0-G2	B2-U0-G2
	Lumens per Watt	116	111	105	100

Energy and Performance Data

Nominal Power Lumens (2200K CCT, 70 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (2700K CCT, 70 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (3000K CCT, 70 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (5000K CCT, 70 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (6000K CCT, 70 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (2700K CCT, 80 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (3000K CCT, 80 CRI)

Number of Light Squares	SA2A	SA2B	SA2C	SA2D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	66	85	111	128
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25