

SKMEI (Model 1266) DIGITAL WATCH INSTRUCTIONS



Four buttons on this watch are known as: **LIGHT**, **MODE**, **RESET**, and **START**

TO SELECT THE DISPLAY MODE

Push the Mode Button in order to select one of the following four display modes in the following order: **Normal Time** -> **Stopwatch** -> **Alarm Set** -> **Time Set**

In the Normal Time Mode, the Day of Week, the Hour, Minute and Seconds are displayed (none flash). If the word Alarm or Chime is displayed, the alarm or hourly chime is turned on.

TO DISPLAY THE ALARM TIME

Press the **MODE** button **x 2**. If the word **ALARM** is displayed the alarm is set. If the word **CHIME** is displayed, the hourly chime is set. **PM** will display for an alarm set after 12pm.

TO STOP/START THE ALARM AND HOURLY CHIME

When viewing the alarm set time, press the **START** button to toggle the alarm and hourly chime on and off.

TO SET THE TIME

Press the **MODE** button **x 3** until the hour is flashing.

To set the **Hour** press the **RESET** button **x 1**. Press the **START** button to increase the hours.

Press the **RESET** button again to toggle through **Minutes** -> **Month** -> **Date** -> **Day of Week** -> **Seconds**

Press the **START** button to increase the setting you are on.

Press **MODE** to complete.

TO SET THE ALARM

Note: The alarm is turned on every time the Alarm is set.

Press the **MODE** button x 2

Press the **RESET** button to set the hour.

Press the **START** button to increase the hours

Press the **RESET** button to select minutes.

Press the **START** button to increase the minutes

A PM indicates PM, blank indicates AM. H indicates a 24 hour clock.

If the time is set as a 24 hour clock, the alarm will also show only as 24 hours with a H.

Press the **MODE** button to finish and return to the time.

TO USE THE STOP WATCH

Press the **MODE** button x 1

Press the **START** button to start timing.

Press the **START** button to stop timing.

Press the **RESET** button to reset the stopwatch to zero.

To record a lap time, press the **RESET** button when the stop watch is running. **SPL** will display and flash. Press **RESET** again to return to the live stopwatch.

