

## FIRMWARE UPGRADE INSTRUCTIONS

For models: BK-22/BK-21A/BK-102A/BK-202A

## Tools Needed:

- Firmware Upgrade Application: "GENERAL\_UPGRADE\_V1.00.15"
- Micro USB Cable

## Firmware File:

• MCU\_MAIN\_HDC-xxx-V1.xx.xx-xxx.bin: MCU Firmware

You can download the Firmware Upgrade File for your respective model in the Downloads section of the Product page. (Please refer images below)

ORE			- Account 🙏 Generit Q. Watties 💟 Cast 🕁 🚘
	PETITING CATEROPER (PALAN) STITUTES RATER CON	THERE REALED UND COMPLETE CONTRACT POLICY	
		2x1 HDMI Switcher W/ Audio Out: 2-In 1- Out, UltraHD 8K, EDID (BK-21A)	
		00000	
		\$79.00	
	- Carlos - C	SKU: BK-21A  Skulich between 2 HDMI Source to 1 display	
	THE CONTRACT OF THE CONTRACT.	Instruct Ausia Intelligit Optical / Analog     Video resolution upto 4Ke)120Hz     Comptiance: HDM121 HDCP 2.3	
	and any set of the set	249 Available in stock	
	and the state	Quantity - I +	
		ADD TO CART	
		Buy with shop Bay	
		C Add to Wishlet	
	🗢 🛋 🚔 🔛 🕯	20 Days Beturn 1 Vear Warranty Pree shipping in USA	
		amazon	
	TRATILES SPECIFICATIONS REVIEWS DOWNLOADS SUPPORT RELATED		
ØREI	SPUTTERS EXTENDERS (BALLIN) SWITCHES MATERX SWITCHES CO	INVERTERS & EXTRACTORS OTHERS PRODUCTS SUPPORT	Accourte 😤 Boorch Q. Wishins 🛇 Con 🕁 🎞
	to with	may with shop Ray	
		Add to Wishlist  Add to Compare	
		30 Dova Return 1 Year Warranty Free shipe in USA	
		amazon	
	See 2 - 2 - 2 - 2 - 2 - 2 - 2 - 2 - 2 - 2	Blow E Y	
	Quick Setup & Installation guide		
	BK 214 User Manual Doverticod		
	Exc-21A Firmware Upgrase Guide		
	EK-20A Firmware Uparade Application		
	gepc2tA firmware upgrode file		

Steps to follow for Firmware Upgrade:

1. Connect your Orei device to a laptop or PC using a Micro USB Cable.



2. Open Firmware Upgrade Application "GENERAL\_UPGRADE\_V1.00.15.exe" and select correct COM port and then set the band rate to "115200".

○ 15	
O IP	🗌 13 Byte
baud rate	
115200 ~	connect
	Search
	Open
	baud rate 115200 ~

3. Select 13 Byte mode then click connect. You will see current Firmware version below.

🙉 General upg	rade tool V1.00.17	_	$\square$ $\times$
СОМ			$\frown$
● COM		Ć	✓ 13 Byte
port	baud rate		
COM4	~ 115200	~	disconnect
IP			
		~	Search
Upgrade			
Open BIN File			Open
	0%		Upgrade
		_	
	MCU: V1.00.0	14	

4. Click open and select correct Firmware Upgrade File, e.g., MCU\_MAIN\_HDC-xxx-V1.xx.xx-xxx.bin and then click upgrade.

👀 General upgra	de tool V1.00.15	- 🗆 ×
сом		
● COM		✓ 13 Byte
port	baud rate	
COM17 -	115200 -	disconnect
IP		
	~	Search
l la succio		
Open BIN	DC-50C22-V2-00-08 bir	Open
File -	DC-3FC22-V2.00.08.DII	Open
	42%	Upgrade
	MCU: V2.00.06	

## 5. Upgrade Done.

随 General upgrad	de tool V1.00.15	- 🗆 X		
COM				
● COM		✓ 13 Byte		
port	baud rate			
COM17 -	115200 -	disconnect		
IP				
	~	Search		
Upgrade Open BIN File V_HDC-SPC22-V2.00.08.bin Open				
	100%	Upgrade		
MCU: V2.00.08				

For any queries, please feel free to contact us at: info@orei.com.

Our team will be more than happy to help you.

