



**Titanium Series T8 15W, 12W, 10W, 8W DIR**  
 For models: 15T8/4F/xxx/DIR, 12T8/4F/xxx/DIR, 10T8/3F/xxx/DIR, 8T8/2F/xxx/DIR  
 Where xxx means 824-965 which indicates CRI and color temperature

**Electronic Ballast Compatibility**

Series	Model	Type	Compatibility
Philips - Advance	ICN-1P32-N	IS	OK w/NOISE
Philips - Advance	ICN-2P32-N	IS	OK w/NOISE
Philips - Advance	ICN-3P32-N	IS	OK w/NOISE
Philips - Advance	ICN-4P32-N	IS	OK w/NOISE
Philips - Advance	IOPA-1P32-LW-N	IS	OK
Philips - Advance	IOPA-2P32-LW-N	IS	OK
Philips - Advance	IOP-2P32-LW-N	IS	OK
Philips - Advance	IOP-4P32-LW-N	IS	OK
Philips - Advance	IOP-3P32-N	IS	OK
Philips - Advance	ICN-132-MC	IS	OK
Philips - Advance	REZ-1S32-SC	PS	OK
Philips - Advance	REZ-2S32-SC	PS	OK
Philips - Advance	VEZ-132-SC	PS	OK
Philips - Advance	VEZ-2S32-SC	PS	OK
Philips - Advance	IZT-132-SC	PS	OK
Philips - Advance	IZT-2PSP32-SC	PS	OK
Philips - Advance	ILV-2S32-SC	PS	OK
Philips - Advance	IOPA-4P32-SC	IS	277V ONLY
Philips - Advance	ICN-4P32-SC	IS	277V ONLY
Philips - Advance	IOP-2P32HL-SC	IS	X
Advance	REL-2P32-SC	IS	X
Advance	REL-2P32-RH-TP	IS	X
GE - Ultramax	GE232MAX-L/ULTRA	IS	OK
GE - Ultramax	GE232MAX-N/ULTRA	IS	OK
GE - Ultramax	GE232MAX-H/ULTRA	IS	OK
GE - Ultramax	GE232MAXP-N/ULTRA	IS	OK
GE - Ultramax	GE232MAXP-H/ULTRA	IS	OK
GE - Ultramax	GE332MAX-N/ULTRA	IS	OK
GE - Ultramax	GE332MAXP-N/ULTRA	IS	3 LAMPS ONLY
GE - Ultramax	GE332MAX-H/ULTRA	IS	OK
GE - Ultramax	GE432MAX-L/ULTRA	IS	OK
GE - Ultramax	GE432MAX-N/ULTRA	IS	OK
GE - Proline	GE-232MV-N	IS	OK
GE - Proline	GE-332MV-N	IS	OK
GE - Proline	GE-432-120-N	IS	OK
GE - Ultrastart	GE-232-120-PS-N	PS	OK
Universal - Triad	B132IUNVHP-N	IS	OK
Universal - Triad	B232IUNVHP-N	IS	OK
Universal - Triad	B332IUNVHP-N	IS	OK
Universal - Ballastar	B232PUS50-A	PS	OK
Plusrite	BAF232IS/MV	IS	OK
Plusrite	BAF432IS/MV	IS	OK
Howard	EP232IS/MV/MC/HE	IS	OK
Howard	EPL332IS/MV/SC/HE	IS	OK
Sylvania	QTP 2x32T8/UNV IS	IS	OK
Sylvania	QTP 2x32T8/UNV ISN-SC	IS	OK
Sylvania	QTP 4x32T8/UNV ISN-SC	IS	OK
Sylvania	QHE 2x32T8/UNV ISN-SC	IS	OK
Sylvania	QHE 2x32T8/UNV ISL-SC	IS	OK
Sylvania	QHE 4x32T8/UNV ISL-SC	IS	OK
Sylvania	QHE 4x32T8/UNV-ISL-SC-1	IS	X
Sylvania	QHE 2X32T8UNVDIMTCL	IS	OK
Sylvania	QHE 4X32T8UNVDIMTCL	IS	OK
Fulham	WHSG4-UNV-T8-IS	IS	OK
Utilitech	YZ-232	IS	OK
EIKO - Powermaster	PM-2x32T8-UNV-IS-L	IS	OK
Espen	VE4P32MVHIPE	IS	OK
Espen	VE3P32MVHIPE	IS	OK
Espen	VE2P32MVHIPE	IS	OK
Espen	VE432MVHIPHE	IS	OK
Espen	VE332MVHIPHE	IS	OK
Espen	VE232MVHIPHE	IS	OK
Espen	VE232MVHRPE	PS	OK
Espen	VE232MVHIPE	IS	OK
Sola	E-758-F-232-SC	IS	X

\*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



### Titanium Series T8 15W, 12W, 10W, 8W DIR

For models: 15T8/4F/xxx/DIR, 12T8/4F/xxx/DIR, 10T8/3F/xxx/DIR, 8T8/2F/xxx/DIR

Where xxx means 824-965 which indicates CRI and color temperature

### Emergency Ballast Compatibility

Brand	Model	Compatibility
Bodine	B54	OK
Bodine	B100	OK
Bodine	B60	OK
Bodine	LP550	OK
Bodine	B30ST	OK
Bodine	LP600	OK
Iota	I-32	OK
Iota	I-320	OK
Iota	I-232	OK
Iota	ISL-54	OK
Iota	ISL-540	OK
Iota	ISD-80	OK
Iota	I-162	OK
Iota	ICE-80	OK
Lithonia	PS1400QD	OK
Lithonia	PSQ500QD	OK
Lithonia	E1500 M12	OK
Fulham	FH3-DUAL-450L	OK
Fulham	FH4-DUAL-700L	OK
Fulham	FH5-DUAL-1400L	OK
ALP	EFP 32GS	OK

**\*GREEN CREATIVE has provided this emergency ballast compatibility chart for guidance when selecting an emergency ballast and lamp combination. Lamps were tested for compatibility with the above listed emergency ballasts. Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.**