

200W DC TO AC POWER INVERTER

DESCRIPTION

DYNAMIX Modified sine wave power inverters include 2x USB ports and standard AC power outlet(s). The DYNAMIX inverters are perfect for charging mobile phones, tablets, notebooks plus many other devices that need power on the go. The DYNAMIX inverters are solid, durable, and built to last. The 2x USB charging ports will detect your devices power requirements and deliver best matched charging current to ensure your device is protected from over-charging or over-loading.

FEATURES

- 200W Modified Sine wave power inverter
- ON/OFF switch. Turns the inverter ON and OFF
- LCD Display
- 1x Standard AC outlet
- 2x USB ports (5V, 2.1A + 1.0A)
- Built-in 12V Connector for on the go power supply
- Cooling fan
- Low voltage alarm
- Overheat and overload protected



PRODUCT CODE

TE6-1621D

DESCRIPTION

200W Power Inverter with LCD display

COLOUR

Black

SPECIFICATIONS

Continues Power	200W
Surge Capacity	400W
AC Output Voltage Range	230V AC
AC Output Frequency	50Hz
Output Waveform	Modified Sine Wave (MSW)
USB Output Ports	2x Ports (3100mAh Shared)
AC Output Socket	1x Standard Port
Battery Low Alarm	10.5V
Low Battery Shut-down	10.5V
Internal Fuse	20A Fuse
Positive Power Input Terminal	No
Negative Power Input Terminal	No
High Speed Cooling Fan	Yes
12V Connector	Yes
Dimensions (LxWxH)	160x120x67mm
Weight	0.7kg

Please note we took the up-most care to compile the information in this datasheet. To the best of our knowledge all info provided were correct at the time of creation. Should any specs change we try to update info accordingly. Information are subject to change without notice. In the case that you find any irregularity please inform our team at contactus@dynamix.co.nz

Last updated: 17 October 2019