

# MX-6224D

DIGITAL MIXER AMPLIFIER 2X240W

## The Ultimate Choice for Mosques

The number of mosques around the world is rapidly increasing however there are very few sound systems that can match their complex needs, as well as their tight budget.

TOA has created the MX-6224D, an affordable digital mixer amplifier, specifically to cater for medium and small mosques. the MX-6224D is a reliable and simple system, needing very little technical knowledge to operate, yet still maintains exceptional sound quality.

---



Article number:MX-6224D 1CE  
Alternative products: MX-6224D, CP-9500M2

---



# MX-6224D

## DIGITAL MIXER AMPLIFIER 2X240W

### Specifications

Power source	220 - 240 V AC, 50 / 60 Hz
Rated output	240 W 2 ch (100 V, 42 Ω, rated output)
Power source	220 - 240 V AC, 50 / 60 Hz
Rated output	240 W 2 ch (100 V, 42 Ω, rated output)
Frequency response	50 Hz - 20 kHz (±3 dB)
Frequency response	50 Hz - 20 kHz (±3 dB)
Power consumption	100 W (according to IEC60065); 570 W (at rated output, both 2 ch)
Distortion	< 1 %
Speaker output	2 zones, 100 V (42 Ohm)
S/N ratio	60 dB
Number of channels	8
Connectable microphones	6
S/N ratio	60 dB
Inputs	MIC 1: -50 dBV (24 V phantom powered) / -60 dBV (phantom power off), 600 Ω, electronically balanced, 6.3 mm phone jack MIC 2 - 4: -66 dBV, 200 Ω, electronically balanced, 6.3 mm phone jack or XLR MIC 5 - 6: -60 dBV, 600 Ω, electronically-balanced, 6.3 mm phone jack or XLR AUX 1: -10 dBV, 10 kΩ mixed monaural, unbalanced, RCA pin jacks (1 pair) AUX 2: -20 dBV, 10 kΩ mixed monaural, stereo mini jack
Outputs	Speaker output: 2 zones, 100V (42 Ohm), galvanic isolated balanced, M4 screw terminal Recording output: 0 dBV, 600 Ohm monaural, unbalanced, RCA pin jacks (1 pair) Effect bus output: 0 dBV, 600 Ohm monaural, unbalanced, RCA pin jacks (1 pair) Preamplifier output: 0 dBV, 600 Ohm monaural, unbalanced, RCA pin jacks (1 each for ROOM and OUTSIDE outputs)
Distortion	< 1 %
Finish	Aluminium, Steel plate, paint, black,
Operating humidity	35% to 80%
Operating temperature	0°C to + 40°C



MX-6224D

# MX-6224D

DIGITAL MIXER AMPLIFIER 2X240W

---

Appearance