

Basic Set Up Guide For ER380/M and ER420M prior to AU versions.

* **Performing the ram clear**

1. Turn Power off to the register (power on/off right hand side)
2. Using the 'C' key insert and turn to the service mode, [one turn past "P" position (6 o'clock)]
3. Whilst the power is off hold down the "Check" key and turn the power back on
4. **!!!!Wait for the beep!!!!** Then release the "check" key
5. Push and release in sequence top left button, bottom left, top right and finally the CASH key. (This will take some time)

NOTE → The ram clear is a key step you should only do this once, as It will delete all data programmed inside the register and set back to the factory default

Turn the **Mode Key** to the **PGM position**

SYSTEM OPTIONS

1. 30 SUBTOTAL
2. 6 X/TIME 1 SUBTOTAL (Allow post tender)
3. 24 X/TIME 3 SUBTOTAL (Activate EJ)
4. CASH to finish

Time & Date

1. 1300 SUBTOTAL
2. HHMM X/TIME
3. MMDDYY X/TIME
4. CASH

PLU STATUS Programming

To program a PLU with a ***preset price And GST***

1. Turn Key to Program Mode
2. 100 Subtotal
3. Push Desired PLU or scan barcode
4. 4 0 0 0 0 0 0 0 0 X/TIME
5. Press **Cash**

To program a PLU with an ***open price and GST***

1. 5 0 0 0 0 0 0 0 0 X/TIME

To program a PLU with an ***open price and without GST***

1. 1 0 0 0 0 0 0 0 0 X/TIME

To program a PLU with a ***preset price and Scaleable NO GST***

6. 1 0 0 0 4 1 0 0 0 X/TIME

PLU DESCRIPTION PROGRAMMING

1. Turn Key Lock to P Position
2. 300 SUBTOTAL
3. Select Plu For description
4. Using the ascii code sheet enter in the description for the PLU (18 Characters MAX)
5. **Or enter using alpha overlay**
6. The X/TIME Key
7. Repeat Steps 1 → 5 until done
8. Cash

PLU PRICE PROGRAMMING

1. 200 SUBTOTAL
2. press item button
3. enter price
4. X/TIME
5. Using the ascii code sheet enter in the description for the group
(Remember only 18 characters)
6. **Or enter using alpha overlay**
7. Subtotal
8. Repeat steps 1 → 5 until done
9. Cash

PC setup on port 1

80 Subtotal 5 x/time 1 CASH CASH

Turn the mode key to back to Register Press 1 Clerk Button and begin operations as normal