

PACKAGING CONTENTS

1. 1 x Light Fitting
2. 1 x Mounting Spike
3. 1 x Pack of Screws



FEATURES

1. "Plug and Play" Installation
2. Built in Photo Electric Cell
3. 6-8hours Operation per day
4. Spike Mounting

INSTALLATION METHOD

1. Remove contents from packaging
2. Locate the "ON/OFF" power switch on the back of your solar panel (See **FIGURE 2**)
3. Switch to "ON" to activate your light (Note, your light is packaged & transported with the power switch in the "OFF" position)

Spike Mount Installation

Refer to **FIGURE 1 & 2** for the following steps

1. Attach mounted base to the bottom of your light fitting using the provided bolt
2. Adjust angle of light to your preference and turn the dial to tighten into place
3. Attach spike mount to the underside of the mounted base
4. To assure your panel is receiving maximum sun exposure, adjust the solar panel using the swivel head to face direct sunlight
5. You can now spike your light into soil or grass and it is ready to go

IMPORTANT NOTES

- **Please ensure you place your solar panel in a location where it can achieve a minimum of 6HRS DIRECT SUNLIGHT**
- Be aware that on overcast/cloudy days, the solar panel will still charge. However, not as efficiently as a sunny day, so the battery may not reach full capacity. Therefore, your light may turn off earlier than specified.
- It's best not to install these lights underneath a street light, porch light etc. because this may stop the automatic day-night sensor triggering and result in your lights not turning on

TROUBLE SHOOTING

Phenomenon	Cause	Inspection Method	Solution
Light won't turn on	Switch hasn't been turned on	Determine what position the switch is in	Turn the switch on
	Battery has run flat	Period of rainy or cloudy weather or installation site doesn't provide enough direct sunlight	Charge the light in direct sunlight for 1-2 days then check again
The light only stays on for a short amount of time	Low Battery	1. Bad installation site for the solar panel 2. Dust or leaves are covering the panel 3. Long period of overcast weather	1. Charge the battery in direct sunlight for 1-2 days with the switch off, then check again 2. Clean the solar panel
	Battery Failure	1. Access the light and & replace battery 2. Battery has matured	Contact SLD Customer Service to buy new batteries

