

TECHNICAL DATA

# Fluke 1660 Series Multifunction Installation Testers



The Fluke 1660 Series Installation Testers are the only installation testers that help prevent damage to connected appliances and also allow users to send test results wirelessly via smartphone directly from the field.



## FLUKE CONNECT™ COMPATIBLE (1664 FC ONLY)

View test results on your smartphone via Fluke Connect™ mobile app and Data Management Software (Fluke TruTest™, sold separately). Download the free Fluke Connect app to enable wireless data transmission and Fluke Cloud™ storage.

## INSULATION PRETEST (1664 FC ONLY)

The Fluke 1660 Series Installation Testers are the only installation testers that help prevent damage to connected appliances.

## AUTO TEST SEQUENCE (1664 FC ONLY)

Start a sequence of seven critical tests with one press of the TEST button.

## HEAVY DUTY, SINGLE INPUT LINE CORD

Guards against failures in the field.

## WARRANTY

Three-year standard warranty.

## Reduce test time up to 40% with Auto Test

Auto Test does 5 required installation tests in one sequence, including selectable Type A, AC & RCD Auto Test, ensuring compliance with local installation regulations. It reduces the number of manual connections, decreases the possibility of making errors and reduces test time up to 40% from previous Fluke models.

## Insulation PreTest

### Protect the installation. Avoid costly mistakes.

The Fluke 1664 FC Installation Tester is the only installation with “Insulation PreTest,” which warns you about potentially serious and costly mistakes. If the tester detects that appliances are connected to the system during test, it will stop the insulation test and provide a visual and audible warning. This helps eliminate accidental damage to peripheral equipment and keeps your customers happy.

## Fluke Connect™, ShareLive™ calling and Fluke Cloud™ storage

### Share from anywhere

Save time—eliminate data entry by wirelessly syncing measurements directly from your installation tester and share with your team using the Fluke Connect system. Having access to measurements simultaneous at the inspection site and from the office or an off-site location enables faster decision making and real time collaboration between team members.

## Fluke Cloud™ storage

### Retrieve stored results from anywhere

Cloud storage allows you to retrieve stored results whether you are in the office or in the field to make decisions in real time. Fluke Connect uses radio-enabled test tools and a mobile app to transfer measurements straight from the field to a secure cloud location, where the data can be accessed by team members. Plus you can import the data into Fluke TruTest™ to process and generate certificates.



**Test EV charging station RCD type A-EV or RDC-DD DC protection devices**

Perform tests on EV charging station DC protection devices using the RCD type B (smooth DC currents) VAR mode, which generates the test currents for RCD type A-EV or RDC-DD acc. to IEC 62955 (6/60/200 mA and ramp <2 to 6 mA ramp). This allows the quick an easy testing of additional 6 mA DC monitors on charging points and can be used in conjunction with the Fluke FEV100 or FEV300 test adapters.

**Key product capabilities**

The 1660 Series testers verify the safety of electrical installations in domestic, commercial and industrial applications. They can ensure that fixed wiring is safe and correctly installed to meet the requirements of IEC 60364 and all relevant local standards.

**Fluke 1664 FC**

The Fluke 1664 FC is the only installation tester that protects connected appliances from damage during insulation tests, and allows you to share your test results wirelessly by smartphone with coworkers or customers. Fluke’s patented Insulation PreTest stops you from performing tests with appliances that are connected to the system during test. This helps eliminate accidental damage and keeps your customers happy.

In addition, the Fluke 1664 FC offers you the power of Fluke Connect. Now you can send test results straight from your Fluke 1664 FC to your smartphone, and transmit those results to other members of your team. You can get feedback, suggestions and even have work orders sent to your job site.

You can also save your test results to Fluke Cloud™ storage. No more writing down data on paper with the possibility of transcription errors. Cloud storage gives you a fast, secure and accurate way to storing all your test data and create test certificates with Fluke TruTest™.

**Fluke 1663**

The ideal tester for professional trouble-shooters. This instrument is ideal for professional users—high-end functionality, advanced measurement capability, yet it is still easy to use. Operation is intuitive and easily mastered by all levels of field workers.

**Fluke 1662**

A solid, basic installation tester. The Fluke 1662 gives you Fluke reliability, simple operation and all the testing power you need for basic installation testing.

**Features by model**

Measurement function	1662	1663	1664 FC
Insulation-PreTest™ safety function			•
Insulation at L-N, L-PE, N-PE inputs			•
Auto Test sequence			•
Loop and line resistance—mΩ resolution			•
Continuity at L-N, L-PE, N-PE inputs		•	•
Test smooth dc sensitive RCDs (Type B/B+)		•	•
EV Test 6 mA (RCD A/EV, RDC-DD) <b>NEW</b>		•	•
Earth resistance		•	•
Voltage trms (ac and dc) and frequency	•	•	•
Wiring polarity checker, detects broken PE and N wires	•	•	•
Insulation resistance	•	•	•
Continuity and resistance	•	•	•
Measure motor windings with continuity test (@ 10 mA)	•	•	•
Loop and line resistance	•	•	•
Prospective Earth Fault Current (PEFC/IK)	•	•	•
Prospective Short-Circuit Current (PSC/IK)	•	•	•
RCD trip time	•	•	•
RCD trip current (ramp test)	•	•	•
Measures trip time and current for RCD type A and AC in one test	•	•	•
RCD variable test current	•	•	•
Automatic RCD test sequence	•	•	•
Phase sequence test	•	•	•

Other features	1662	1663	1664 FC
Fluke Connect™ compatibility			•
ShareLive™ calling			•
Fluke Cloud™ storage			•
On/Off switchable Auto Start for RCD and Loopstest	•	•	•
Self-test	•	•	•
Illuminated display	•	•	•
Memory, interface			
Z Max memory		•	•
Memory		•	•
IR-USB and BLE interface for use with optional Fluke TruTest™ or FVF Software	IR-USB	IR-USB	IR-USB/BLE
Included Accessories			
Heavy duty mains cord with single input connector	•	•	•
Hard case	•	•	•
Remote control probe	•	•	•
Zero adapter	•	•	•

### General specifications

Specification	Characteristic
Size	10 cm (L) x 25 cm (W) x 12.5 cm (H)
Weight (incl. batteries)	approx. 1.3 kg
Battery size, quantity	1.5 V type AA (IEC LR6), 6 pcs.
Sealing	IP 40
Safety	Complies with IEC/EN61010-1, UL61010, ANSI/ISA –s82.02.01 and CAN/CSA c22.2 No. 1010
Overvoltage	CAT III 500 V, CAT IV 300 V
Performance	EC/EN61557-1 to IEC/EN61557-7 and IEC/EN61557-10

### AC and DC voltage measurement trms

Range	Resolution	Input Impedance	Overload Protection
500 V	0.1 V	3.3 MΩ	660 V rms

### Continuity testing (R<sub>LO</sub>)

Range (Autoranging)	Resolution	Open Circuit Voltage
20 Ω/200 Ω/2000 Ω	0.01 Ω/0.1 Ω/1 Ω	> 4 V

### Insulation resistance measurement (R<sub>ISO</sub>)

Test voltages	
1662	1663/1664 FC
100-250-500-1000 V	50-100-250-500-1000 V

Test Voltage	Insulation Resistance Range	Resolution	Test Current
50 V	20 MΩ/50 MΩ	0.01 MΩ/0.1 MΩ	1 mA @ 50 kΩ
100 V	20 MΩ/100 MΩ	0.01 MΩ/0.1 MΩ	1 mA @ 100 kΩ
250 V	20 MΩ/200 MΩ	0.01 MΩ/0.1 MΩ	1 mA @ 250 kΩ
500 V	20 MΩ/200 MΩ/500 MΩ	0.01 MΩ/0.1 MΩ/1 MΩ	1 mA @ 500 kΩ
1000 V	20 MΩ/200 MΩ/1000 MΩ	0.01 MΩ/0.1 MΩ/1 MΩ	1 mA @ 1 MΩ

**Insulation pretest**

Insulation safety pretest	Requires to connect the Tester to L, N and PE.
---------------------------	--

**Loop and line impedance (Z<sub>l</sub>)**

Range	Resolution
10 Ω (Hi current mΩ mode)/20 Ω/200 Ω/2000 Ω	1 mΩ/ 0.01 Ω/ 0.1 Ω/1Ω

**Prospective earth fault current, PSC test**

Range	Resolution
1000 A/10 kA (50 kA)	1 A/0.1 kA

**Computation:** Prospective Earth Fault Current (PEFC) or Prospective Short Circuit Current (PSC) determined by dividing measured mains voltage by measured loop (L-PE) resistance or line (L-N) resistance, respectively.

**RCD testing, RCD types tested**

RCD Type		Model 1662	Models 1663/1664 FC
AC <sup>1</sup>	G <sup>2</sup> , S <sup>3</sup>	A/F <sup>4</sup> , AC <sup>1</sup> , G <sup>2</sup> , S <sup>3</sup>	A-EV/RDC-DD <sup>5</sup> , A/F, AC, B/B+ <sup>5</sup> , G, S

<sup>1</sup>Responds to AC. <sup>2</sup>General, no delay. <sup>3</sup>Time delay. <sup>4</sup>Responds to pulsed signal. <sup>5</sup>Responds to smooth dc signal.

**RCD trip time test (ΔT)**

Current Settings <sup>1</sup>	Multiplier	Measurement Range		
		RCD Type G	RCD Type S	EV / RDC-DD
10-30-100-300-500-1000 mA – VAR	x ½, x 1	310 ms	510 ms	N/A
10-30-100 mA	x 5	50 ms	160 ms	N/A
6, 60, 200 mA	VAR mode type B	N/A	N/A	6 mA - 10 s 60 mA - 0.3 s 200 mA - 0.1 s

<sup>1</sup>1000 mA type AC only. 700 mA maximum type A in VAR mode, VAR mode at RCD type B (smooth dc currents) generates the test currents acc. to IEC 62955 for RCD type A-EV or RDC-DD (6/60/200 mA and ramp <2 to 6 mA).

**RCD trip current measurement/ramp test (I<sub>ΔN</sub>)**


Current Range	Step Size	Dwell Time		Measurement Accuracy
		Type G	Type S	
30% to 110% of RCD rated current <sup>1</sup>	10% of I <sub>ΔN</sub> <sup>2</sup>	300 ms/step	500 ms/step	+/- 5%
<2 mA to 6 mA smooth dc <sup>3</sup>	linear rising within 30s	N/A	N/A	+/- 5%
<b>Notes</b> 30% to 210% for Type A I <sub>ΔN</sub> = 10mA 20% to 210% for Type B		<b>Specified trip current ranges (EN 61008-1):</b> 50% to 100% for Type AC 35% to 140% for Type A (>10 mA) 35% to 200% for Type A (≤10 mA) 50% to 200% for Type B		

<sup>1</sup>30% to 150% for Type A I<sub>ΔN</sub> > 10 mA. <sup>2</sup>5% for Type B. <sup>3</sup>For RCD type A-EV/ RDC-DD acc. to IEC 62955.

**Earth resistance test (RE) Model 1664 FC and 1663 only**

Range	Resolution	Frequency	Output Voltage
200 Ω/2000 Ω	0.1 Ω/1Ω	128 Hz	25 V

**Phase sequence indicaton**

Icon 	Range	Display
Phase Sequence indicator is active	100 to 500 V	"1-2-3": or "3-2-1"



**Included Accessories**

6x AA (IEC LR6) cell batteries,  
C1600 hard carrying case, zero  
adapter, heavy duty mains cord,  
STD standard test lead set,  
padded carrying and waist strap,  
quick reference guide, TP165X  
remote control probe and lead set  
(FTP/UK fused probes, UK only).

**Ordering Information**

**Fluke 1664 FC** Multifunction  
Installation Tester with Auto Test,  
Insulation PreTest, Fluke  
Connect™ compatibility

**Fluke 1663** Multifunction  
Installation Tester

**Fluke 1662** Multifunction  
Installation Tester

**Preventive maintenance simplified. Rework eliminated.**

Save time and improve the reliability of your maintenance data by wirelessly syncing measurements using the Fluke Connect™ system.

- Eliminate data-entry errors by saving measurements directly from the tool and associating them with the work order, report or asset record.
- Maximize uptime and make confident maintenance decisions with data you can trust and trace.
- Access baseline, historical and current measurements by asset.
- Move away from clipboards, notebooks and multiple spreadsheets with a wireless one-step measurement transfer.
- Share your measurement data using ShareLive™ video calls and emails.
- **Fluke 1664 FC** is part of a growing system of connected test tools and equipment maintenance software. Visit the website to learn more about the Fluke Connect™ system.

Find out more at [flukeconnect.com](http://flukeconnect.com)



All trademarks are the property of their respective owners. WiFi or cellular service required to share data. Smartphone, wireless service and data plan not included with purchase. First 5 GB of storage is free. Phone support details can be viewed at [fluke.com/phones](http://fluke.com/phones).

**Smartphone wireless service and data plan not included with purchase.**  
**Fluke Connect™ is not available in all countries.**

**CalMet.ie**

Instrument Calibration & Sales

☎ +353 (0)1 450 9095 ✉ [hello@calmet.ie](mailto:hello@calmet.ie)

**Fluke.** *Keeping your world up and running.*

[www.fluke.com](http://www.fluke.com)

©2023 Fluke Corporation.  
Specifications subject to change without notice.  
230250-en

**Modification of this document is not permitted without written permission from Fluke Corporation.**