

FIELD RADIO S450DLX

AM/FM/Shortwave Field Radio with Liquid Crystal Display

Features

- AM/MW (520-1710 KHz / 522-1620 KHz), FM (88-108 MHz), SW (continuous frequency range from 1711-29999kHz)
- Frequency Tuning Steps: 3 methods to choose from (fast/slow/stop)
- Analog tuning with digital display
- High performance IC and MOSFET: Provides high sensitivity, strong anti-interference, low background noise and lower distortion.
- MW/SW IF wide/narrow bandwidth selection: improves audio fidelity and minimizes noise.
- MCU Control (micro controller unit) and large LCD backlight display with: frequency, clock, battery level indicator, and signal strength indicator
- AM band features dual conversion PLL technology: provides anti-image rejection.
- 50 station memory (10 presets for each band)
- Dual alarm with wakeup, snooze, and sleep functions
- AM/FM/SW external antenna input socket and the ability to connect to cable FM.
- Individual MW 500 Ext./GND socket for external antenna and ground to improve MW sensitivity
- Strap type carrying handle
- Full-range speaker with variable independent bass and treble control
- Stereo line level audio input/output and Stereo/Mono selection
- Power source: 6 x D batteries (not included) or DC IN (9V) , negative polarity, 500 mA adapter
- Includes: owner's manual, warranty card, AC adapter

Dimensions: 12.2" x 7.6" x 3.9" (W x H x D)

310 x 195 x 100 mm (W x H x D)

Weight: 3.59 lbs. (1.63 kg)

* Specifications subject to change



Digital Tuner



Receives AM/FM Band



Receives Shortwave Band



Alarm Clock



Audio Line Input



Headphone Jack



* Actual product may vary

GRUNDIG

Etón Corporation
1015 Corporation Way
Palo Alto, CA 94303-4305 USA

To Order:
1.800.793.6542
www.etoncorp.com

eton
EMPOWERED BY NATURE

© Copyright 2011 Etón Corporation. All Rights Reserved.