

MODEL: RECESSED LIGHT CONVERSION KIT (RLC)

ASSEMBLY INSTRUCTIONS

1. Install the RLC kit per the manufacturer's instructions.
 - Install cover plate (A) before installing mounting plate (AA).
 - Do not install decorative medallion (B) (not shown).
3. Make electrical connections according to fixture installation instructions with the following modifications:
 - Hot (black) and neutral (white) connections are made to the pig-tail connector (M) (not shown) from the RLC kit.
 - Connect the ground wire from the lamp cord to the bare copper wire from the RLC kit.
4. Mount canopy plate (BB) along with the completed fixture assembly (not shown) to mounting plate (AA) using finials (CC).

IMPORTANT SAFETY INSTRUCTIONS

CAUTION: Only use E26 (Type A) bulbs rated 100W or less for incandescent, 10W or less for LED. Exceeding the maximum bulb wattage may result in an electrical hazard.

CAUTION: Turn the power off before replacing the bulb. Ensure the bulb has had sufficient time to cool down as it may be hot to the touch.

Only use a dry, soft, lint-free cloth to clean the fixture and glass shade. Refer to the FAQ section of the Bicycle Glass website for further details.

