

INSTRUCTION GUIDE

Residential Garden Spot Light

Model No.SLDGS0053-WW, SLDGS0053-CW, SLDGS0053-RGB

PACKAGING CONTENTS

- 1 x Light Fitting
- 1 x Mounting Spike
- 1 x Pack of Screws



FEATURES

1. Day/Night Sensor
2. High/Low Brightness Setting
3. 8 hours Operation per day
4. Spike or Surface-Mount Option
5. Adjustable Solar Panel
6. Colour –Black

INSTALLATION METHOD

1. Remove contents from packaging
2. Locate the **“ON/OFF”** power button on the back of your solar panel
3. Press the **“ON/OFF”** button once, the light will be set at **“LOW”** level (Dim). Press the button again and the light will be at **“HIGH”** level (Bright). Press the button a third time and your light will be **“OFF”**

(Note, your light is packaged & transported with the power button in the **“OFF”** position).

Spike Mount Installation

*Please refer to **FIGURE 1** for the below steps*

1. Attach mounting spike to the bottom of your light fitting
2. To assure the panel is receiving maximum sun exposure, adjust the solar panel using the swivel head to face direct sunlight
3. Spike your garden light into soil or grass and it is ready for use

IMPORTANT NOTES

- **Please ensure you place your solar panel in a location where it can achieve a minimum of 6HRS DIRECT SUNLIGHT**
- **If you wish for longer illumination throughout the night, switch the light to “LOW” mode**
- Be aware that on overcast/cloudy days, the solar panel will still charge. However, not as efficiently as a sunny day, so the battery may not reach full capacity. Therefore, your light may turn off earlier than specified.
- It's best not to install these lights underneath a street light, porch light etc. because this may stop the automatic day-night sensor triggering and result in your lights not turning on

TROUBLE SHOOTING

Phenomenon	Cause	Inspection Method	Solution
Light won't turn on	Switch hasn't been turned on	Determine what position the switch is in	Turn the switch on
	Battery has run flat	Period of rainy or cloudy weather or installation site doesn't provide enough direct sunlight	Charge the light in direct sunlight for 1-2 days then check again
The light only stays on for a short amount of time	Low Battery	1. Bad installation site for the solar panel 2. Dust or leaves are covering the panel 3. Long period of overcast weather	1. Charge the battery in direct sunlight for 1-2 days with the switch off, then check again 2. Clean the solar panel
		Battery Failure	1. Access the light and & replace battery 2. Battery has matured

