

Installation: It is good wiring practice to make all the connections with the "+" contact on the lightstrip to the red or copper colored wire, and the "-" contact on the lightstrip to the white or blue colored wire. In "AC" systems this doesn't matter, but in "DC" systems it does, and many power supplies are "DC"

Tapewire: Stick the ExtraBrite lightstrip onto the tapewire with a contact lined up with each strip of foil. Punch a hole thru each contact with an EL-66 Electrification tool, and insert an eyelet thru the contact into the foil.



Solid Wire: Stick the ExtraBrite lightstrip onto any non-conductive surface. Drill or punch a hole thru the two outer contacts with the EL-66 Electrification tool. Insert the bare end of a solid wire into, the holes and insert an eyelet to <u>secure</u> the wire.



See also RGT's #E239 Striplight Connector



ExtraBrite Strips use under 3 watts/foot visit www.dhbuilder.com for more info