

EL-DMXC-192CH

LED DMX Operator 192-Channel Controller


SPECIFICATION SHEET

JOB NAME: LOCATION: QUOTE/REF#:



SPECIFICATIONS

Input Voltage:	9V-12V DC, (220 mA min.)
Included:	Power Supply 120V or 220V operation (not multi-voltage)
Dimensions:	5.25 in. L x 19 in. W x 2.5 in. H - 19 in.
	482.6 mm L x 133.35 mm W x 63.5 mm H
Weight:	5 lbs
Warranty:	2 Year Limited



DESCRIPTION

Step 1 Dezigns DMX Operator controls up to 192 DMX channels. You can record up to 6 chases which you can then playback with separate fade and step speeds. The 8 individual faders provide easy controllability for any DMX 512 intelligent fixture.

It has 12 individual fixture buttons that allow you to control up to 12 separate intelligent lighting fixtures of up to 16 DMX channels each. With Step 1 Dezigns DMX Operator Controller, you can record up to 6 chases with separate fade times and step speeds. The 8 individual channel faders provided you with easy controllability of any DMX512 moving light.

Need help with your LED lighting applications? Our lighting experts are here to help! Contact us today for assistance with lighting plan or installation instructions.

KEY FEATURES

- Control up to192 DMX channels
- Control up to 12 separate intelligent lights with up to 16 DMX channels per fixture
- Fixtures with less than 16 DMX channels may be combined on 1 fixture button to optimize channel space
- Record up to 6 programmable chases with separate fade times and step speeds
- 8 individual faders give you easy channel control for your intelligent light or dimmer packs
- MIDI controllable
- DMX-512, 3-pins XLR signal
- Built-in Microphone for chase step activation

APPLICATIONS

- Trade Show & Exhibit Lighting
- Retail Display Lighting
- Architectural Lighting
- Hotels, Casinos, and Clubs
- Custom Lighting Shows
- Stage Lighting