



4 hours In-Wall Preset Countdown Timer Switch

Model No: HET06-R

Description

Wiring your lights or fan through a preset timer switch like the Enerlites HET06 can help save you money while adding a level of convenience and energy saving to your home. This Enerlites preset timer switch has the time adjustment from 5, 10, 30, 60, 2 hours and 4 hours. This unit works with incandescent, fluorescent lamp and fan motor; ideal for closet, pantry, garage, laundry room, basement, outdoor lighting, and home spas.

Features

- Seven buttons preset timer switch.
- For use with incandescent, fluorescent lights, and fan motor.
- Replace standard light or fan single pole switch.
- Sleek design mounts flush with wall plate.
- Blue LED indicator for time duration

Testing & Code Compliance



Specifications

Voltage	120VAC @ 60Hz
Tungsten	1200W
Resistive	1200W
Fan motor	1/2HP
Time delay	5, 10, 30, 60 mins, 2, 4 hours
Colors Available	White and Ivory

Wiring Diagram

