



# CANOPY INSTALLATION DIAGRAM

1. Turn off power circuit
2. Tie overhand knot inside the canopy
3. Locate the positive (black), negative (white) and ground (green or bare copper) in the junction box and at the end of the cloth covered wire.
4. Strip end of wires to expose the stranded copper wire.



5. Connect matching wires with wire connectors and wrap secure with electrical tape
6. Secure mounting plate to ceiling
7. Secure canopy to mounting plate



8. Tighten the plastic set screw of the canopy cord grip firmly in to the color cord.



## WARNING

Turn off power at circuit before wiring and always consult a licensed electrician.