	U			Dimmer Co	mpatibility	y for Green	Lux Par20 6.	.5W 120V/60HZ	2700K 36D	Ra>80	
No.	Brand		Model	1 lamp	2 lamps	3 Lamps	4 Lamps	5 Lamps	6 Lamps	7 lamps	8 lamps
1	LUTRON		CTCL-153P	$\checkmark$							
2	LUTRON		RRD-6NA-WH	Dimmer is broken,can't test.							
3	LUTRON		D-600P	0	0	0	0	0	0	0	0
4	LUTRON		SELV-300P	$\checkmark$							
5	LUTRON	A second second	DVELV-300P	$\checkmark$							
6	LUTRON		S-600	$\checkmark$	$\checkmark$	$\checkmark$	0	0	0	0	0
7	LUTRON		D-600PH-DK	×	×	×	×	×	×	×	×
8	LUTRON		NLV-600	$\checkmark$							
9	LUTRON		VTELV-600M-B	$\checkmark$							
10	LUTRON		DVCL-153P	$\checkmark$							
11	LUTRON		LG-603P	$\checkmark$							
12	LUTRON		S-600P	$\checkmark$							
13	LEVITON		IPI06-1LZ	$\checkmark$	$\checkmark$	0	0	0	0	0	0
14	LEVITON		6613-PL	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	0	0
15	LUTRON		S-603PG	$\checkmark$							
16	LEVITON		6681	×	×	×	×	×	×	×	×
17	LEVITON	-100	6161- <b>W</b>	$\checkmark$	~	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$
18	LUTRON		AY-600P	$\checkmark$	~	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$
19	LUTRON	1	NLV-1000	$\checkmark$							
20	LEVITON		6633-P0G	$\checkmark$							
21	LUTRON		MAELV-600-WH	Dimmer is broken,can't test.							
22	LUTRON		DV-600P	$\checkmark$							
23	LUTRON		LGCL-153PL	$\checkmark$	$\checkmark$	$\checkmark$	~	~	$\checkmark$	$\checkmark$	$\checkmark$
24	LEVITON		IPE04-1LZ	$\checkmark$	$\checkmark$	$\checkmark$	~	~	$\checkmark$	$\checkmark$	$\checkmark$
25	LUTRON		RRD-10ND	$\checkmark$	$\checkmark$	$\checkmark$	~	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$
26	LUTRON		MA-600	$\checkmark$							
27	LEGRAND		LS603PWV	$\checkmark$	$\checkmark$	$\checkmark$	~	$\checkmark$	$\checkmark$	$\checkmark$	$\checkmark$
28	LUTRON		MACL-153M	$\checkmark$							

REMARK: JWORKING VERY WELL; O WHEN ADJUST TO THE LOW BRIGHTNESS RANGE: SLIGHT FLICKING (Acceptable); XWHEN ADJUST TO THE LOW BRIGHTNESS RANGE: FREQUENTLY FLICKING (Unacceptable)

1 MEAN 1 DIMMER TAKE 1 LAMP, 8 MEAN 1 DIMMER TAKE 8 LAMP.