

INSTALLATION INSTRUCTIONS

FOR CHAIN HUNG (MODEL: 9094-95)

WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER.

AVERTISSEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.

- Carefully unpack your new fixture and lay out all the parts on a clear area. Make sure not to misplace any small parts necessary for installation.
- Provide a 1/4 IPS pipe with one end securely mounted to a beam or a structural member. The other end should protrude through the center of the outlet box as shown.
- Assemble the loop, nipple, nuts, hickey and spacer to center 1/4 IPS support pipe and adjust overall length to allow the loop to hold the canopy flush to the ceiling. When the adjustments have been completed, secure the nuts.
- Attach the chain to the fixture loop with quick link. Slip the collar nut and canopy over the upper end of the chain. Then attach the chain to loop with quick link.
- Lace the electric wire, bare copper wire and safety cable through the chain and loop, exiting through the side of hickey. Place the safety cable through the lock and coil the hickey twice in circle, through the top of the outlet box and secure to structural member.
- Connect the electric wire and make sure that all the wire connector are secured. If your outlet box has a ground wire (green or bare copper), connect the ground wire to it. If not, connect the fixture ground wire directly to the junction box. After all the wires are connected, tuck them carefully inside the outlet box.
- Raise the ceiling canopy and the screw collar nut up to ceiling and secure to screw collar loop. Make sure the weight of the chain-hung fixture is supported by the chain, not the electric cord.
- Install the light bulbs from the hinged door upon removing the bolt up and down to open the door. In accordance with the fixture specification.

DO NOT EXCEED RECOMMENDED WATTAGE! (NE PAS DEPASSER LA PUISSANCE NOMINALE MAXIMALE!) CAUTION: RISK OF FIRE, CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT CIRCUIT CONDUCTOR. MIN. 90 C SUPPLY CONDUCTORS--ATTENTION - RISQUE D'INCENDIE, CONSULTER UN ÉLECTRICIEN QUALIFIÉ POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DÉRIVATION SONT ADÉQUATS.

“CAUTION-RISK OF FIRE CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT BRANCH CIRCUIT CONDUCTOR”

ATTENTION – RISQUE D'INCENDIE, CONSULTER UN ÉLECTRICIEN QUALIFIÉ POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DÉRIVATION SONT ADÉQUATS.







Fig.3



Notice: It is important to use proper chain pliers (not included) To OPEN and CLOSE the chain included with this fixture. Do not open them with other tools that may twist or stress the chain links. It is important to use proper chain pliers like the ones shown in the diagram.

U.S. Patent No: D438,660
 This product is protected by United States Federal and/or State Law, including Patent and/or Copyright laws.
 © Minka Lighting Inc.