

Digital Multimeter


DM-98

HTCTM
INSTRUMENTS



Features :

- 3½ Digit
- 6000 Count
- Dual LCD with Bargraph
- Live test (sound and light alarm)
- NCV
- True RMS
- Double color backlight
- Torch



DC VOLTAGE

Range	Resolution	Accuracy
600mV	0.1mV	±0.5% of rdg + 3 digits
6V	0.001V	
60V	0.01V	
600V	0.1V	
1000V	1V	

AC VOLTAGE

Range	Resolution	Accuracy
600mV	0.1mV	±0.8% of rdg + 5 digits
6V	0.001V	
60V	0.01V	
600V	0.1V	
750V	1V	

FREQUENCY / DUTY

Range	Resolution	Accuracy
10Hz	0.1Hz	±1.0% of rdg + 3 digits
100Hz	0.001kHz	
1kHz	0.01kHz	
10kHz	0.1kHz	
100kHz	0.1kHz	
1MHz	0.001MHz	
10MHz	0.001MHz	

DC CURRENT

Range	Resolution	Accuracy
600uA	0.1uA	±1.2% of rdg + 3 digits
6000uA	1uA	
60mA	0.01mA	
600mA	0.1mA	
10A	0.01A	

AC CURRENT

Range	Resolution	Accuracy
600uA	0.1uA	±1.5% of rdg + 3 digits
6000uA	1uA	
60mA	0.01mA	
600mA	0.1mA	
10A	0.01A	

TEMPERATURE

Range	Resolution	Accuracy
-20~0°C		±5% of rdg + 3 digits
0~400°C	1°C	±1.0% of rdg + 2 digits
400~1000°C		±2.0% of rdg
-4~32°F		±5.0% of rdg + 6 digits
32~752°F	1°F	±1.0% of rdg + 4 digits
752~1832°F		±2.0% of rdg

RESISTANCE

Range	Resolution	Accuracy
600Ω	0.1Ω	±1.0% of rdg + 3 digits
6kΩ	0.001kΩ	
60kΩ	0.01kΩ	
600kΩ	0.1kΩ	
6MΩ	0.001MΩ	
60MΩ	0.01MΩ	±1.5% of rdg + 3 digits

CAPACITANCE

Range	Resolution	Accuracy
10nF	0.001nF	±4.0% of rdg + 5 digits
100nF	0.01nF	
10μF	0.1nF	
10mF	0.001μF	
100μF	0.01μF	
100mF	0.1μF	
1000mF	0.001mF	±5.0% of rdg + 5 digits
1000μF	0.01mF	

INPUT JACK LED INDICATOR

Range	Resolution	Accuracy
Diode test		✓
Continuity Buzzer		✓
Power	AA1.5V X 2	
Standard Accessories : Manual, Test Lead		
Dimension : 188(H) x 88(W) x 58(D) mm		

Special Function :



INPUT JACK LED INDICATOR