4 Troubleshooting

Fault diagnosis – flashing code (LED with series resistor)

The electronic control box can store up to 5 faults.


The defective component and type of fault are output by the control box as a flashing code and are displayed by an LED with series resistor (approx. 1 k Ω / 1W).

The LED with series resistor is connected to the 8-pin connector of the heater cable harness (chamber 2, cable 1² bl/ws and chamber 5, cable 1² ge).

The flashing codes of the defective components and the corresponding fault codes are described on page 14.


Possible causes and remedial action are explained in the fault code tables (pages 22 – 25).

LED and series resistor



Sketch 7

Flashing code



Sketch 8