


PATRIOT SERIES


Faulty Pendant Bypass Testing

Helps determine if pendant is faulty

- To Test: 1) You will need two 6" jumper wires 14AWG up to 22AWG
 2) Strip both ends of jumper wire approximately 3/4"
 3) Take Female Control Box Plug and follow below to test each function of hoist.
 If all Up, Down and Fast Functionality works properly during testing, you may have an issue with the pendant. Note: The pendant runs on low voltage




Plug Schematic




Ground to Down to Test Down



Ground to Up to Test Up



Ground to Down to Test Down
Ground to Fast to Test Fast Down



Ground to Up to Test Up
Ground to Fast to Test Fast Up