



The Transceiver Module works in conjunction with a handheld wireless remote controller such as the X-10 PRO 16-Plus Remote (PHR02 or PHR03) to control lights and appliances from up to 100ft away, even through walls. As well as its built-in switched outlet, the Transceiver Module controls up to 15 additional X-10 modules via the powerline. The transceiver Module can also be controlled by other X-10 powerline controllers such as the X-10 PRO Mini Controller (PHC01).

The Transceiver Module is designed to control loads with the following ratings:

Resistive load	15A
Motor load	1/3 HP
Incandescent load	500W
TV/Stereo	400W

### Setting up Transceiver Module

- Set the Transceiver's House Code dial to match the House Code on the remote controller that will be used with it.
- Set the UNIT slide switch to "1" to control the built in outlet from a transmitter or controller sending a command to unit 1, or "9" to control the built in outlet with control 9. Either position allows control of all 16 unit numbers from the X-10 PRO 16-Plus Remote Control (PHR02).
- Plug a lamp or appliance into the Transceiver Module and plug the Transceiver Module into a convenient AC outlet.

### Local control

An ON-OFF button is provided on the Transceiver Module which toggles the output, of the built-in switched outlet, from ON to OFF and vice versa when pressed.