

EAGLE 1500

USER MANUAL

THANK YOU FOR PURCHASING BLUE BADGER LIGHTS PRODUCTS

Main Features

- 1500 Lumens MAX illumination
- Luminus SST-20 LED with a lifespan of 50,000 hours
- 1-18650 Samsung 3500mAh Power Cell rechargeable Li-ion battery included
- Maximum beam distance up to 456 meters
- 5 brightness levels and 2 Special modes (Strobe/SOS)
- Tactical tail switch with Momentary-on function
- Instant access to MAX and Special modes
- Gold spring-loaded impact absorption with double O-ring seals
- USB-C direct charging port, charging cable included
- Power indicator built into the Mode button indicates remaining 20% battery power
- Memory function for brightness levels and special modes
- Constructed from T6-6061 heat treated aluminum alloy
- IPX5 rated
- Impact resistant to 2 meters
- Tail stand capability

Dimensions

Length: 6.01" (155mm) Head diameter: 1.38" (35mm) Tail diameter: 1" (25.4mm)
Weight: 3.92oz (111g without battery) 5.50z (156g with battery)

Operating Instructions

*** Prior to first use, unscrew rear section of light and remove the plastic battery insulator, replace rear section and fully tighten.

***Battery is not shipped fully charged.

ON/Off/Momentary ON/Operation:

To switch ON: Press the Tail Button once, repeat to turn OFF, or triple click the blue Mode button for OFF.

Momentary ON: Press the tail switch partway down and hold to momentarily turn the light on. Release the tail switch to turn the light off.

Brightness Levels MAX-1500/High- 600/Mid-400/ Low-150/Eco-35:

With the Eagle switched on, press the blue Mode button repeatedly to cycle through the following brightness levels: MAX, High, Medium, Low, and Eco.

Special modes (Strobe/SOS):

With the light switched ON, double press the BLUE Mode button to enter Strobe mode, double press again to exit. When in strobe mode, press the Blue Mode button again to activate SOS. To exit double press the MODE button.

Instant MAX Output:

With the light ON, press and hold the BLUE Mode button for one second to access MAX mode (1500 lumens).

Memory Mode:

Method 1: Switch the light on and select desired mode; Using the Tail Button switch the light OFF. Switch the light ON with the Tail Button, light returns to previous mode.

Method 2: Switch the light on and select desired mode; Triple press the Blue Mode button the light turns OFF. Press Mode button again light returns to previous mode.

Maintenance

Every 6 months, threads should be wiped with a clean cloth followed by a thin coating of silicon-based lubricant.

Warranty Service

All BLUE BADGER LIGHTS products are warranted for quality and workmanship. Any defective BLUE BADGER LIGHTS product can be repaired free of charge for a period of 60 months (5 years) from the date of purchase. Beyond 60 months (5 years), a limited warranty applies, covering the cost of labor.

Our warranty is void in all of the following situations:

- 1.The product(s) is/are broken down, reconstructed and/or modified by unauthorized parties.
- 2.The product(s) is/are damaged through improper use.
- 3.The product(s) is/are damaged by leakage of batteries.







For the latest information on BLUE BADGER LIGHTS products and services, send an email to Info@bluebadgerlights.com. This user manual is for reference purpose only. Any discrepancy between this manual and information contained on www.bluebadgerlights.com, our official website shall prevail.

BLUE BADGER LIGHTS has the right to interpret and amend the content of this document at any time without prior notice.

Smoking Monkey Solutions, Inc. *dba* BLUE BADGER LIGHTS

TEL: +1 904-770-5249
E-mail: info@bluebadgerlights.com
Web: www.bluebadgerlights.com
Address : 3501-B N. Ponce De Leon Blvd.
St. Augustine, FL 32084

OUTPUT AND RUNTIME

	MAX	HIGH	MED	LOW	ECO	STROBE/SOS
 LUMENS	1500	600	400	150	35	1500
	1 HR 60MIN	2 HR 48MIN	6 HR 36MIN	48 HR	2 HR / 4 HR	
	456 METERS					
						
	2 METERS					
	IPX5					

Battery Charge Indicator:

The Eagle 1500 features an LED power indicator built into the Blue Mode Button. Fully charged, the button will be completely blue. When 20% battery capacity is reached, the LED indicator will begin to flash and dim as the battery depletes.

Charging:

First turn the flashlight on, triple click the blue Mode button, then plug the USB port of the charging cable into an electrical wall charger, then connect the Micro USB-C port of the charging cable into the light. The Mode Button light will display red while charging, and will turn to solid blue when fully charged. Remove the USB-C cable and re-install the rubber dust cover on the light. Normal charging time is 1.5 hours. Charging with the light switched on is not recommended. Doing so may cause extended charging time or less fully charged battery.

Battery Replacement:

Unscrew the tail cap to insert the battery with the (+) side towards the light head, then screw the tail cap back on.

Battery Specifications:

Use 18650 Samsung 3500 mAh Power Cell batteries with installed protective chip (UL listed, UN38.3 & MSDS certified). Lesser quality batteries may damage the light and void the warranty.