


You have decided to buy a watch, which was assembled by a watchmaker using a Ronda movement. Please note that no watches are produced or distributed under the Ronda brand.

In case of repairs, guarantee claims and questions concerning the functioning of a watch, purchasers and consumers should contact their retailer or the watch manufacturer, for which the relevant information can be found in the sales or guarantee documentation provided with the watch.

Description of the display and control buttons



Setting the time

- 1* Pull out the crown to position III (the watch stops).
- 2 Turn the crown until you reach the correct time 8:45.
- 3* Push the crown back into position I.

Please note:
* In order to set the time to the exact second, 1* must be pulled out when the second hand is in position «60». Once the hour and minute hands have been set, 3* must be pushed back into position I at the exact second.

Setting the date (quick mode)

- 1 Pull out the crown to position II (the watch continues to run).
- 2 Turn the crown anticlockwise until the correct date @II appears.
- 3 Push the crown back into position I.

Please note:
During the date changing phase between approx. 8 PM and 12 PM, the date must be set to the date of the following day.
An extreme acceleration in setting the date with quick mode can induce a false date indication. The synchronization is re-established by setting the date from 01 till 31 (crown in position II).

Setting the date, day of the week (8040.N), time

Example:
- Date / time on the watch: 17 / 01:25 / MON
- Present date / time: 23 / 20:35 / SAT

- 1 Pull out the crown to position III (the watch stops).
- 2 Turn the crown until yesterday's day of the week FRI appears.
- 3 Push the crown to position II.
- 4 Turn the crown anticlockwise until yesterday's date appears 22.
- 5* Pull out the crown to position III (the watch stops).
- 6 Turn the crown until the correct date 23 and day of the week SAT appears.
- 7** Continue to turn the crown until the correct time 8:35 PM appears.
- 8 Push the crown back into position I.

Please note:
* To set your watch to the exact second, please refer to the chapter entitled «setting the time».
** Please observe the AM/PM clock rhythm.

Chronograph: Basic function
(Start / Stop / Reset)

Example:
1 Start: Press push-button A.
2 Stop: stop the timing, press push-button A once more and read the chronograph counters: 4 min / 38 sec / 1/2 sec
3 Zero positioning: Press push-button B. (The chronograph hands will be reset to their zero positions.)

Chronograph: Accumulated timing

Example:
1 Start: (start timing)
2 Stop: (e.g. 15 min 5 sec following 1)
3 Restart: (timing is resumed)
4* Stop: (e.g. 5 min 12 sec following 3) = 20 min 17 sec (The accumulated measured time is shown)
5 Reset: The chronograph hands are returned to their zero positions.

Please note:
* Following 4, the accumulation of the timing can be continued by pressing push-button A (Restart / Stop, Restart / Stop, ...).

Chronograph: Intermediate or interval timing

Example:
1 Start: (start timing)
2 Display interval: e.g. 20 minutes 17 seconds (timing continues in the background)
3 Making up the measured time: (the chronograph hands are quickly advanced to the ongoing measured time.)
4 Stop: (Final time is displayed)
5 Reset: The chronograph hands are returned to their zero position.

Please note:
* Following 3, further intervals or intermediates can be displayed by pressing push-button B (display interval / make up measured time, ...).

Adjusting the chronograph hands to zero position

Example:
One or several chronograph hands are not in their correct zero positions and have to be adjusted (e.g. following a battery change).

- 1 Pull out the crown to position III (all chronograph hands are in their correct or incorrect zero position.)
- 2 Keep push-buttons A and B depressed simultaneously for at least 2 seconds (the second counter hand rotates by 360° → corrective mode is activated.)

Adjusting the second counter hand
Single step: A 1 x short
Continuous: A long

Adjusting the next hand B
Single step: A 1 x short
Continuous: A long

Adjusting the 1/2 second counter hand (position 3h)
Single step: A 1 x short
Continuous: A long

Adjusting the next hand B
Single step: A 1 x short
Continuous: A long

Adjusting the minute counter hand (position 9h)
Single step: A 1 x short
Continuous: A long

Returning the crown to position I
Termination of the chronograph hands adjustment (can be carried out at any time).