

## PBX Guide

### Adding Extension

Click **Accounts** and select **Extensions**

Extension Add

**BACK** **SAVE**

Extension	<input type="text"/>	Set extension number
	<small>Enter the alphanumeric extension. The default configuration allows 2 - 7 digit extensions.</small>	
Number Alias	<input type="text"/>	
	<small>If the extension is numeric then number alias is optional.</small>	
Range	<input type="text" value="1"/>	Set extension range (multiple extensions)
	<small>Enter the number of extensions to create. Increments each extension by 1. <input type="checkbox"/> Auto-generate user with extension as login name</small>	
Voicemail Password	<input type="text"/>	Set numeric voicemail password
	<small>Enter the numeric voicemail password here.</small>	
Effective Caller ID Name	<input type="text"/>	Set extension internal caller id name
	<small>Enter the internal caller ID name here.</small>	
Effective Caller ID Number	<input type="text"/>	Set extension internal caller id number
	<small>Enter the internal caller ID number here.</small>	
Outbound Caller ID Name	<input type="text"/>	Set extension outbound caller id name
	<small>Enter the external (public) caller ID name here.</small>	
Outbound Caller ID Number	<input type="text"/>	Set extension outbound caller id number
	<small>Enter the external (public) caller ID number here.</small>	
Emergency Caller ID Name	<input type="text"/>	
	<small>Enter the emergency caller ID name here.</small>	
Emergency Caller ID Number	<input type="text"/>	
	<small>Enter the emergency caller ID number here.</small>	
Directory Full Name	<input type="text"/>	
	<small>Enter the first name followed by the last name.</small>	
Directory Visible	<input type="checkbox" value="True"/>	
	<small>Select whether to hide the name from the directory.</small>	
Directory Extension Visible	<input type="checkbox" value="True"/>	
	<small>Select whether announce the extension when calling the directory.</small>	
Limit Max	<input type="text" value="5"/>	
	<small>Enter the max number of outgoing calls for this user.</small>	
Limit Destination	<input type="text"/>	
	<small>Enter the destination to send the calls when the max number of outgoing calls has been reached.</small>	
Voicemail Enabled	<input type="checkbox" value="True"/>	
	<small>Enable/disable voicemail for this extension.</small>	
Voicemail Mail To	<input type="text"/>	Set extension email address if you want to receive voicemail via email
	<small>Enter the email address to send voicemail to (optional).</small>	
Voicemail File	<input type="text" value="Audio File Attachment"/>	
	<small>Select a listening option to include with the email notification.</small>	
Voicemail Keep Local	<input type="checkbox" value="True"/>	
	<small>Choose whether to keep the voicemail in the system after sending the email notification.</small>	
Call Timeout	<input type="text" value="30"/>	
	<small>Enter the call timeout.</small>	
Call Group	<input type="text"/>	
	<small>Enter the user call group here. Groups available by default: sales, support, billing.</small>	
Record	<input type="checkbox" value="Disabled"/>	Select the extension call record
	<small>Choose whether to record local, inbound, outbound, or all.</small>	
Call Timeout	<input type="text" value="30"/>	
	<small>Enter the call timeout.</small>	
Call Group	<input type="text"/>	
	<small>Enter the user call group here. Groups available by default: sales, support, billing.</small>	
Record	<input type="checkbox" value="Disabled"/>	
	<small>Choose whether to record local, inbound, outbound, or all.</small>	
Hold Music	<input type="text" value="Default"/>	
	<small>Select the MOH Category here.</small>	
<b>ADVANCED</b>		
Enabled	<input type="checkbox" value="True"/>	
	<small>Set the status of the extension.</small>	
Description	<input type="text"/>	

**SAVE**

Click **SAVE** to save changes