	Flick	Flick Duo	The Controller	FLUX Φ	SensaVox	AXIS
Outputs	Single Output	Dual Output	Single Output	Dual Output	Dual Output	Dual Output
Power	70mA	70mA	80mA	125mA	125mA	125mA
Intensity Levels	24	25	18	99	99	99 (since update 1.1)
Number of Modes	2	2	3	6	3	7
Pre-programmed patterns	7	8	7	30+	9	30+
Accelerometer	Analog	Analog	Omni-directional vibration sensor	12-bit triple axis	N/A	12-bit triple axis
Proximity Sensor	No	No	No	No	No	Yes
Contactless 'Gesture' Control	No	No	No	No	No	Yes
Audio Control (Line-In and Microphone)	No	No	No	Yes- Digital Stereo	Yes- Mono	Yes- Digital Stereo
Battery	USB Rechargeable Lithium-ion - Approx 6 hours playtime from 3 hour charge (dependent on intensity)	USB Rechargeable Lithium-ion - Approx 3 hours playtime from 3 hour charge (dependent on intensity)	**Remote:** 1.5V LR1/910A/N-Cell **Stimulator:** 9V - Play-time variable using battery (depends on battery quality) and intensity levels	USB Rechargeable Lithium-ion - Up to 8 hours play-time from a single charge (dependent on mode and intensity) - Charges to 80% in under an hour - Graphic battery gauge	9V battery or mains powered - Play-time variable using battery (depends on battery quality) and intensity levels	USB Rechargeable Lithium-ion - Up to 8 hours play-time from a single charge (dependent on mode and intensity) - Charges to 80% in under an hour - Graphic battery gauge
Display	LED lights	7-segment LED	LED lights	OLED digital display (black and white)	7-segment LED	OLED digital display (blue)
Updatable (PC only)	No	No	No	Yes via USB- performance fixes and maintenance (FREE)	No	Yes via USB- mode updates/new features/maintenance (FREE)
Configuration Menu for User Specific Settings	No	No	No	Yes	No	Yes
Warranty	1 year as standard 3 years when registered for free	1 year as standard 3 years when registered for free	1 year as standard 3 years when registered for free	1 year as standard 3 years when registered for free	1 year as standard 3 years when registered for free	1 year as standard 3 years when registered for free