
# shiloori

Design by Kateřina Handlová



bommo

Installation Manual for Pendant Light Fixtures

#### Introduction

- Please read this user's manual carefully prior to installation and follow its instructions and recommendations.
- The installation of the pendant light requires more than one person.
- For safety reasons, as well as for warranty purposes, it is forbidden to use this product in breach of this manual and other purposes stipulated in this manual.
- Prior to assembly, use an appropriate circuit breaker to turn off electricity.
- All interventions regarding the wiring of the light fixture may only be carried out by a qualified electrician.
- Prevent children or persons with lowered sensory or psychological abilities from handling
  the light fixture, as it contains small and fragile pieces that could be dangerous when
  inappropriately handled or ingested.
- The producer bears no liability for damage caused by improper installation.
- The dimensions and weight of glass parts may differ slightly due to manual production.
- All Bomma products are made from hand-blown lead-free crystal. Any small bubbles, non-melts and inhomogeneities in the glass are not a reason for complaint. This is a characteristic feature of this traditional craft.
- The surface of the mounting may also include minor imperfections due to manual production.
- · The pendant light is intended for interior lighting.

#### Components included in the package

- Hand-blown glass part of the light fixture (1x, 3x or 5x depending on the type selected)
- Mounting (1x, 3x or 5x depending on the selected type)
- Rope for hanging the fixture (1x, 3x or 5x depending on the type selected)
- Ceiling hooks (1x, 3x or 5x depending on the type selected)
- Dimmable light source (1x, 3x or 5x depending on the type selected)
- Installation manual
- Maintenance instructions
- Gloves

### Technical parameters, specifications

- Voltage input: 230 V / A.C. 50Hz
- · Protection: IP 20
- Input power Shibari 1: 1x LED lamp max. 6.5 W (E27)
- Input power Shibari 3: 3x LED lamp max. 6.5 W (E27)
- Input power Shibari 5: 5x LED lamp max. 6.5 W (E27)
- · Cable lenght: 2,5 m
- Weight Shibari 1: ~ 5 kg
- Size Shibari 1: dia. 170mm, H 700 mm
- Weight Shibari 3: ~ 15 kg
- Size Shibari 3: 3 x dia. 170mm, H 700 mm
- Weight Shibari 1: ~ 25 kg
- Size Shibari 5: 5 x dia. 170mm, H 700 mm
- Light source: T30 x 300, 6W LED, 380 lm, 2700 K, RA 90+
- · Class: I.

↑↓ 300 mm

Ø 30 mm


Recommended light source: LED E27, max. 6.5 W.



Upon opening, first determine that there was no damage occurred during transport and that the light fixture is complete. Otherwise, please contact your seller immediately, as later claims may not be considered.

Assemble the lighting fixture according to the manual, recognizing that its installation wiring may only be carried out by a qualified electrician following general legal regulations.


Slip the plate (1) on the incoming power supply cable from the ceiling and attach using appropriate screws and wall-plugs, which are not included in the package. Select their size and type according to the material of your wall or ceiling and the weight of the fixture.






Attach the hooks 2 to the ceiling. Make sure the cable can reach from the hanging glass part to the mounting plate.

If you are installing a Shibari fixture with only one glass part, skip this step.






Slide the cable/cables 7 through the canopy 3 and secure by tightening the plastic grommets.





Install the wiring according to the diagram.







Attach the canopy  $\ensuremath{\ensuremath{\mathfrak{G}}}$  to the mounting plate using nuts  $\ensuremath{\ensuremath{\mathfrak{B}}}.$ 




Insert a dimmable light source  $\ensuremath{\mbox{\@red}}$  into the socket  $\ensuremath{\mbox{\@red}}$  .








Attach the ring  $\circ$  onto the throat of the glass part 4.






Slide the light bulb (5) into the glass part (4). Tighten the screws (13) on the cap (11) using the openings in the glass part.






Slide the rope 0 through the loop 9 in the ring using a "cow hitch" knot as shown in the diagram.





Slide both ends of the rope (1) through the loop of the canopy. When installing a Shibari with three or five glass parts, loop the rope through the ceiling hook (3).






Slide the ends of the rope (10) under the weave surrounding the glass and tie a tight knot.

Congratulations! You may now reconnect the power and turn the light on.

When dismantling, first turn off the light and disconnect from the power supply. Then follow the above steps in reverse order. Use the original or similar packaging for possible later transport of the light fixture to prevent damage.



#### Maintenance

- When unpacking, installing and cleaning your fixture, handle the individual components with outmost care, particularly the glass parts, which are very fragile.
- Assembly and electric installation must be carried out by certified electricians.
- · Pendant lights are intended for interiors.
- We recommend consulting the installation and the anchoring of pendant lights in ceiling materials with your project manager, technician or another competent party.
- Do not cover nor touch the light source while the light is on.
- Do not attempt any repairs or changes to the components. Always contact our specialized service.
- Spare parts that are not supplied or approved by the producer may not be used (with the exception of light sources replacement).
- Do not expose the light fixture to unsuitable environments where it could become damaged (water, frost, heat).
- Ensure appropriate access (ladder, scaffolding, aerial work platform) prior to maintenance or cleaning pendant lights, in order to comfortably reach and safely handle the light fixture.
- Note: in some areas, the lighting fixture may have sharp edges that may cause injury. Beware while in immediate proximity of the fixture.
- Perform cleaning and all maintenance with the light turned off, ideally entirely disconnected. Respect this rule for the entire duration of installation.
- When changing a light bulb, always disconnect the light fixture from its power supply.
- We recommend hanging the fixture up at sufficient height to avoid injury (e.g. head injury) to persons moving within its proximity.
- We recommend performing the installation of pendant lights with more than one person.
- · After installation check whether the light

- fixture is properly set in its base.
- Do not expose the light to inappropriate strain and protect it from mechanical damage.
- When in operation, the light source becomes hot. Prior to any handling, wait for the light source to naturally cool down and do not expose it to fast cooling.
- Halogen light sources may not come in contact with greasy materials, so do not touch them with bare hands. Install them using clean textile gloves or tea towels.
   When cleaning halogen bulbs, it is best to use alcohol-based cleaners.
- When changing a bulb, use the same or recommended light source. Information regarding the type appears both on the label and in the installation manual.
- Do not hang any other components on the light fixture, other than those listed in the installation manual.
- Pay attention to checking all parts prior to their installation. Damaged components and glass parts (fragmentation, cracks) may cause personal injuries to persons moving within its proximity.
- Should any serious problem occur during cleaning or maintenance, do not hesitate to contact the producer.
- Any other handling of the pendant light fixture should be performed by a qualified technician or directly by the producer.

#### Cleaning

- All cleaning and maintenance must be carried out when the power is off, ideally entirely disconnected.
- When cleaning, use fine-fabric gloves.
   Particularly avoid handling metalcoated crystal without gloves to avoid fingerprints and loss of gloss.
- Use soft cloths to clean metal parts. Such parts may be cleaned with a dry cloth or a cloth dampened in warm water with a mild detergent. Avoid the use of solvents or technical benzene to clean metal parts. Avoid alcohol-based cleaners that may cause changes of surface colors.
- Clean light bulb using a soft dampened cloth, antistatic brush with soft bristles or a vacuum cleaner turned to low mode.
- Clean fine-steel surfaces with products sold especially for this purpose.
- To clean the glass parts, use products in concentrations recommended by their producers. Immediately after cleaning, dry the light fixture and hang it again.
- When cleaning glass parts, a concentrate
  of 90% water and 10% vinegar may also
  be used. Fill up a clean spray-bottle with
  this mixture. Use cotton gloves, apply the
  solution to one of them and gently wipe
  the parts requiring cleaning. Immediately
  dry the cleaned surfaces with the other
  glove. Give particular care to cleaning
  individual parts of the light that cannot
  be dismantled. Inappropriate handling
  may cause loosening or chipping of
  these parts.
- Avoid cleaning removable parts of the light fixture in a dishwasher.

#### Important notice

- The producer bears no responsibility for damage caused by unprofessional installation or inappropriate handling of the light fixture, including installation with accessories other than those recommended by the producer.
- The producer bears no responsibility for damage caused by unprofessional interventions into the mounting and safety features of the light fixture, including damage to the product by inappropriate power supply, storage or use of the light fixture in a humid environment.
- Do not place the light fixture in humid environments, such as near a boiler or other sources of water vapor. Do not place the lighting fixtures in shower enclosures or above bathtubs and never touch them when you are in contact with water.
- The producer reserves the right to make minor changes to the construction of the light fixture without prior notice.

## Disposal

Upon the completion of the technical working life of the light fixture and its disconnecting from power supply, dismantle and separate the individual parts. Hand over the separated parts to the appropriate organizations responsible for waste disposal.

# **Waste Materials Catalog**

Number	Category	Name	
10 11 11*	N	Waste glass	
		in small particles	
		and glass powder	
		containing heavy metals	
10 11 12	0	Waste glass other than those	
		mentioned in 10 11 11	
17 04 01	0	Copper, bronze, brass	
17 04 05	0	Iron and steel	
20 01 01	0	Paper and cardboard	
15 01 05	0	Composite packaging	

#### Contact

Bohemia Machine Ltd. 1177 Zámecká St 58291 Světlá nad Sázavou Czech Republic +420 569 453 149 info@bomma.cz www.bomma.cz

**Instagram** bomma\_cz Facebook bommacz

# bomma.cz











Control	Date of packaging	