

SONIXINEMA

INTIMATE LEGATO SERIES

User Manual

Table of Contents

Note From The Creators	3
Instrument Description	4
Library Format	4
The Instrument	5
Microphones	5
GUI	5
Global Tab	6
Mix Tab	7
Envelope Tab	8
FX Tab	9
Filter Controls	9
Tape Controls	9
Reverb Controls	9
Delay Controls	10
Chorus Controls	10

Note From The Creators

Congratulations and thank you for taking your time to check out our instruments and purchasing an Intimate Legato instrument. We would like you to know that we wholeheartedly appreciate your trust and support, and we hope you will find our instrument useful and inspiring. If you have any questions or concerns do not hesitate to reach out via our online chat or email us directly to support@sonixinema.com

Happy playing!

All the very best,
Tomas & Louis

Instrument Description

We have designed and built a dedicated powerful sampling engine with an intuitive interface and true legato performance. It allows the user to perform and adjust the sound much further. It offers a variety of sound shaping tools, including a Proximity fader which smoothly blends across several microphone setups, and a custom on-board effects unit.

We recommend that you fully read the manual to understand and explore capabilities of the instrument, as we are certain you will learn some tricks that you otherwise wouldn't know about.

Library Format

Intimate Legato instruments require Native Instruments Kontakt, version 6.7.1 and up. If you do not own Native Instruments Kontakt, you can download a FREE Kontakt Player to use this instrument.

If this is the first time you are using Kontakt it is recommended that you read the Kontakt Manual.

The Instrument

Intimate Legato interface was built specifically to accommodate this unique instrument, its character and tone.

Microphones

Offers magnificent sonic flexibility to anyone from film score composers to music producers and even sound designers. We recorded and mixed focusing on performance and its details as well as constructing multiple perspectives, covering everything from extreme close up for those that require an upfront, closely captured textures, to traditional film score perspectives. To achieve the set goal, a total of 6 microphones were used and then mixed into a total of 4 different perspectives. *Close Mono, Close Stereo, Mid, Far* and a separate combined mix. All microphone position mixes are accessible via Mix Page with dedicated volume fader, solo and mute buttons.

GUI

Our new GUI allows intuitive control over the microphone positions via the 'Proximity' fader which morphs between available microphone positions, as well as providing access to individual microphones. All of this is complemented by a large array of effects including a convolution reverb with a selection of custom designed Impulse Responses as well as natural, real lush spaces.



Page Navigation Bar

You will notice that the main window is split into two halves, allowing the user to move between pages more intuitively when shaping the sound. The available pages on the left - Global, Mix. Then, the Envelope and Effects page on the right. Simply click on the icon to select which page you want to see on either of the GUI sides.

To help you navigate through the parameters, there is a parameter display in the bottom left corner which will display a parameter name that you engaged with and its value.

Parameter display:



Via Kontakt's display options and enabling the "Info". Once enabled the hits will appear at the bottom of the Kontakt interface.



Global Tab

Proximity. Allows the user an 'easy mix' solution. Users can move between all available microphone position mixes, from Close (fader is all the way up) to Far (fader is all the way down).

For more in-depth control over each perspective there are faders for each of them on the Mix Page where each one of the faders be Soloed or Muted, and attenuated independently. More about the Mix Page below.

Detune. Determines the tuning of the samples. The slider moves in increments of a semitone. If alt/option is held, the user can select a value in cents (between integral multiples of one semitone).

Expression. *Note: mapped to #CC1 (Mod Wheel) by default.*

Legato Toggle Switch. Switch between Legato and Sustains. Sustains allow multiple notes to be played at once to form chords.

Legato Intensity. Adjust the volume of the legato transitions.

Legato Speed. Adjust the speed of the legato transitions.

Stereo Width. Used to narrow down the stereo field, or completely fold down to mono. Also available on the Mix Page. Default position: 100% Stereo

Blur. As the name suggests this control allows the user to add some blur and roundness to the sound.

Gloss. As the name suggests this parameter allows the user to add some air and gloss to the sound.



Mix Tab

1- 5. Perspective Faders. Controls the level of each microphone mix/perspective. Changing the value of the Proximity fader will affect the positions of the perspective faders, but not vice-versa.


6. Solo/Mute (button). Solos or mutes the respective channel.

7. Stereo Width (knob). Used to narrow down the stereo field, or completely fold down to mono. This mirrors the value of the mono/stereo width knob on the Global panel.

Default position: 100% Stereo (Ctrl + Click snap to default)

8. RAM switch (button). Switches between load all samples and load only required samples. If active, only the necessary samples are loaded (as defined by the Proximity and individual mic position faders). If inactive, then all samples are always loaded.

9. Mix. It is a combination of all the microphones, therefore it has not been intended to be used at the same time as other perspectives. But there is no reason why you can't if you want! Please note, it is not part of the proximity.



Envelope Tab

Instruments sound, volume intensity and spectral content changes over time. ADSR (Attack, Decay Sustain and Release) allows you to control the shape of sound through its duration.

Attack time is the time taken for initial run-up of level from nil to peak, beginning when the key is first pressed.

Decay time is the time taken for the subsequent run down from the attack level to the designated sustain level.

Sustain level is the level during the main sequence of the sound's duration, until the key is released.

Release time is the time taken for the level to decay from the sustain level to zero after the key is released.

Amp ADSR

Full range traditional Attack, Decay, Sustain and Release controls.

Filter ADSR

Full range traditional ADRS controls. Used to control filter behaviour upon each keystroke.


With the help of the filter envelope you can determine the time in which the filter is open and the time at which it will close when you press the key.

Pitch ADSR

Full range traditional ADRS controls. Used to control samples pitch upon each keystroke.

Filter/Amp Link (button)

If active, changes to the filter controls will be mirrored by the amp controls, and vice versa.



FX Tab

Effects page is divided into 6 separate areas, each of which is dedicated to a particular effects unit.

Filter Controls

Compact set of controls that affect the parameters for three different filters (*LP* – *Low Pass*, *BP* – *Band Pass*, *HP* – *High-Pass*). Only one is shown/modified at a time, but all three filters can be active at the same time. When ON, filter button will turn light.

1. On/Off (button). Turns the effect on or off.
2. Frequency. Displayed filter's cutoff frequency.
3. Resonance. Displayed filter's resonance amount.
4. Filter Select (push buttons). Determines the filter whose parameter values are displayed, and gives an indication of which filters are active. Illuminated text = filter is on.



Tape Controls

A set of controls that determine Tape Saturators parameters. Multiple saturation types are available, but only one is active at a time.

5. Tape Type Selector (push buttons). Determines the saturation type that is active, and whose parameter values are displayed.
6. Saturation Amount. Determines the amount of tape saturation effect. A = Classic; B = Enhanced; C = Transient
7. Degrade Amount. Determines the level of the degradation effect. Effect is switched off if knob is turned all the way to the left and automatically switches on as the knob is turned right.

Reverb Controls

A set of controls that determine the parameters of the convolution reverb.

8. On/Off (toggle button). Turns the effect on or off.
9. Reverb Amount. determines the level of reverb.
10. Reverb Size control. Determines the size of the reverb.
11. Reverb Pre-Delay. Determines the amount of reverb pre-delay.
12. IR Select (menu). Displays a selection of IR's supplied with the instrument. Included IR's cover vast array of designed, experimental and natural spaces.

Delay Controls

A set of controls that determine the parameters of the delay effect.

13. On/Off (toggle button). Turns the effect on or off.

14. Delay Amount (knob). Determines the level of the delay.

15. Delay Time (knob). Determines the time parameter of the delay.

26. Delay Feedback (knob). Determines the amount of delay feedback.

27. Delay free/sync (toggle button). Toggles the delay time parameter units between ms and beats. If set to beats, then the time parameter is displayed/defined in beats and synced to the host tempo.

Chorus Controls

A set of controls that determine the parameters of the chorus effect.

On/Off (toggle button). Turns the effect on or off.

Chorus Amount (knob). Determines the level of the chorus effect.

Chorus Depth (knob). Determines the amount of depth in the chorus effect.

Chorus Speed (knob). Determines the speed of the chorus effect.